

NQC Programmer's Guide

Version 3.1 r5

by Dave Baum & John Hansen

Contents

1	Introduction	1
2	The NQC Language	2
2.1	Lexical Rules	2
2.1.1	Comments	2
2.1.2	Whitespace	3
2.1.3	Numerical Constants	3
2.1.4	Identifiers and Keywords	3
2.2	Program Structure	4
2.2.1	Tasks	4
2.2.2	Functions	5
2.2.3	Subroutines	8
2.2.4	Variables	9
2.2.5	Arrays	11
2.3	Statements	11
2.3.1	Variable Declaration	11
2.3.2	Assignment	12
2.3.3	Control Structures	13
2.3.4	Access Control and Events	16
2.3.5	Other Statements	18
2.4	Expressions	18
2.4.1	Conditions	20
2.5	The Preprocessor	21
2.5.1	#include	21

2.5.2	#define	21
2.5.3	Conditional Compilation	22
2.5.4	Program Initialization.....	22
2.5.5	Reserving Storage	22
3	NQC API.....	24
3.1	Sensors	24
3.1.1	Types and Modes RCX, CM, Spy.....	25
3.1.2	Sensor Information.....	27
3.1.3	Scout Light Sensor Scout	28
3.1.4	Spybotics Sensors Spy.....	29
3.2	Outputs	30
3.2.1	Primitive Calls	30
3.2.2	Convenience Calls.....	31
3.2.3	Global Control RCX2, Scout, Spy	33
3.2.4	Spybotics Outputs	35
3.3	Sound	35
3.4	LCD Display RCX.....	37
3.5	Communication.....	38
3.5.1	Messages RCX, Scout.....	38
3.5.2	Serial RCX2, Spy	40
3.5.3	VLL Scout, Spy.....	49
3.6	Timers	49
3.7	Counters RCX2, Scout, Spy	50
3.8	Access Control RCX2, Scout, Spy	51

3.9	Events RCX2, Scout	51
3.9.1	Configurable Events RCX2, Spy	52
3.9.2	Scout Events Scout.....	57
3.10	Data Logging RCX	59
3.11	General Features	61
3.12	RCX Specific Features.....	63
3.13	Scout Specific Features	63
3.14	CyberMaster Specific Features.....	64
3.15	Spybotics Specific Features.....	66
3.16	Swan Specific Features	82
4	Technical Details	97
4.1	The asm statement	97
4.2	Data Sources.....	98

1 Introduction

NQC stands for Not Quite C, and is a simple language for programming several LEGO MINDSTORMS products. Some of the NQC features depend on which MINDSTORMS product you are using. This product is referred to as the *target* for NQC. Presently, NQC supports six different targets: RCX, RCX2 (an RCX running 2.0 firmware), CyberMaster, Scout, Spybotics, and Swan (an RCX running Dick Swan's enhanced firmware).

All of the targets have a bytecode interpreter (provided by LEGO) which can be used to execute programs. The NQC compiler translates a source program into LEGO bytecodes, which can then be executed on the target itself. Although the preprocessor and control structures of NQC are very similar to C, NQC is not a general purpose language - there are many restrictions that stem from limitations of the LEGO bytecode interpreter.

Logically, NQC is defined as two separate pieces. The NQC language describes the syntax to be used in writing programs. The NQC API describes the system functions, constants, and macros that can be used by programs. This API is defined in a special file built in to the compiler. By default, this file is always processed before compiling a program.

This document describes both the NQC language and the NQC API. In short, it provides the information needed to write NQC programs. Since there are several different interfaces for NQC, this document does not describe how to use any specific NQC implementation. Refer to the documentation provided with the NQC tool, such as the *NQC User Manual* for information specific to that implementation.

For up-to-date information and documentation for NQC, visit the NQC Web Site at <http://bricxcc.sourceforge.net/nqc>

2 The NQC Language

This section describes the NQC language itself. This includes the lexical rules used by the compiler, the structure programs, statements, and expressions, and the operation of the preprocessor.

2.1 Lexical Rules

The lexical rules describe how NQC breaks a source file into individual tokens. This includes the way comments are written, then handling of whitespace, and valid characters for identifiers.

2.1.1 Comments

Two forms of comments are supported in NQC. The first form (traditional C comments) begin with `/*` and end with `*/`. They may span multiple lines, but do not nest:

```
/* this is a comment */

/* this is a two
   line comment */

/* another comment...
   /* trying to nest...
      ending the inner comment...*/
   this text is no longer a comment! */
```

The second form of comments begins with `//` and ends with a newline (sometimes known as C++ style comments).

```
// a single line comment
```

Comments are ignored by the compiler. Their only purpose is to allow the programmer to document the source code.

2.1.2 Whitespace

Whitespace (spaces, tabs, and newlines) is used to separate tokens and to make programs more readable. As long as the tokens are distinguishable, adding or subtracting whitespace has no effect on the meaning of a program. For example, the following lines of code both have the same meaning:

```
x=2;  
x = 2 ;
```

Some of the C++ operators consist of multiple characters. In order to preserve these tokens whitespace must not be inserted within them. In the example below, the first line uses a right shift operator ('>>'), but in the second line the added space causes the '>' symbols to be interpreted as two separate tokens and thus generate an error.

```
x = 1 >> 4; // set x to 1 right shifted by 4 bits  
x = 1 > > 4; // error
```

2.1.3 Numerical Constants

Numerical constants may be written in either decimal or hexadecimal form. Decimal constants consist of one or more decimal digits. Hexadecimal constants start with 0x or 0X followed by one or more hexadecimal digits.

```
x = 10; // set x to 10  
x = 0x10; // set x to 16 (10 hex)
```

2.1.4 Identifiers and Keywords

Identifiers are used for variable, task, function, and subroutine names. The first character of an identifier must be an upper or lower case letter or the underscore ('_'). Remaining characters may be letters, numbers, and an underscore.

A number of potential identifiers are reserved for use in the NQC language itself. These reserved words are called keywords and may not be used as identifiers. A complete list of keywords appears below:

```
__event_src      __res            __taskid        abs  
__nolist        __sensor        __type          acquire
```

asm	do	int	sub
break	else	monitor	switch
case	false	repeat	task
catch	for	return	true
const	goto	sign	void
continue	if	start	while
default	inline	stop	

2.2 Program Structure

An NQC program is composed of code blocks and global variables. There are three distinct types of code blocks: tasks, inline functions, and subroutines. Each type of code block has its own unique features and restrictions, but they all share a common structure.

2.2.1 Tasks

The RCX implicitly supports multi-tasking, thus an NQC task directly corresponds to an RCX task. Tasks are defined using the `task` keyword using the following syntax:

```
task name()
{
    // the task's code is placed here
}
```

The name of the task may be any legal identifier. A program must always have at least one task - named "main" - which is started whenever the program is run. The maximum number of tasks depends on the target - the RCX supports 10 tasks, CyberMaster supports 4, Scout supports 6, and Spybotics supports 8.

The body of a task consists of a list of statements. Tasks may be started and stopped using the `start` and `stop` statements (described in the section titled *Statements*). There is also a NQC API command, `StopAllTasks`, which stops all currently running tasks.

2.2.2 Functions

It is often helpful to group a set of statements together into a single function, which can then be called as needed. NQC supports functions with arguments, but not return values. Functions are defined using the following syntax:

```
void name(argument_list)
{
    // body of the function
}
```

The keyword `void` is an artifact of NQC's heritage - in C functions are specified with the type of data they return. Functions that do not return data are specified to return `void`. Returning data is not supported in NQC, thus all functions are declared using the `void` keyword.

The argument list may be empty, or may contain one or more argument definitions. An argument is defined by its *type* followed by its *name*. Multiple arguments are separated by commas. All values are represented as 16 bit signed integers. However NQC supports six different argument types which correspond to different argument passing semantics and restrictions:

Type	Meaning	Restriction
<code>int</code>	pass by value	none
<code>const int</code>	pass by value	only constants may be used
<code>int &</code>	pass by reference	only variables may be used
<code>const int &</code>	pass by reference	function cannot modify argument
<code>int*</code>	pass pointer	only pointers may be used
<code>const int *</code>	pass pointer	function cannot modify pointer argument

Arguments of type `int` are passed by value from the calling function to the callee. This usually means that the compiler must allocate a temporary variable to hold the argument. There are no restrictions on the type of value that may be used. However, since the function is working with a copy of the actual argument, any changes it makes to the value will not be seen by the caller. In the example below, the function `foo` attempts to set the value of its argument to 2. This is perfectly legal, but since `foo` is working on a copy of the original argument, the variable `y` from main task remains unchanged.

```
void foo(int x)
{
    x = 2;
}

task main()
{
    int y = 1; // y is now equal to 1
    foo(y);    // y is still equal to 1!
}
```

The second type of argument, `const int`, is also passed by value, but with the restriction that only constant values (e.g. numbers) may be used. This is rather important since there are a number of RCX functions that only work with constant arguments.

```
void foo(const int x)
{
    PlaySound(x); // ok
    x = 1;        // error - cannot modify argument
}

task main()
{
    foo(2);      // ok
    foo(4*5);    // ok - expression is still constant
    foo(x);      // error - x is not a constant
}
```

The third type, `int &`, passes arguments by reference rather than by value. This allows the callee to modify the value and have those changes visible in the caller. However, only variables may be used when calling a function using `int &` arguments:

```
void foo(int &x)
{
    x = 2;
}

task main()
{
    int y = 1; // y is equal to 1

    foo(y);    // y is now equal to 2
    foo(2);    // error - only variables allowed
}
```

The fourth type, `const int &`, is rather unusual. It is also passed by reference, but with the restriction that the callee is not allowed to modify the value. Because of this restriction, the compiler is able to pass anything (not just variables) to functions using

this type of argument. In general this is the most efficient way to pass arguments in NQC.

There is one important difference between `int` arguments and `const int &` arguments. An `int` argument is passed by value, so in the case of a dynamic expression (such as a sensor reading), the value is read once then saved. With `const int &` arguments, the expression will be re-read each time it is used in the function:

```
void foo(int x)
{
    if (x==x) // this will always be true
        PlaySound(SOUND_CLICK);
}

void bar(const int &x)
{
    if (x==x) // may not be true..value could change
        PlaySound(SOUND_CLICK);
}

task main()
{
    foo(SENSOR_1);    // will play sound
    bar(2);          // will play sound
    bar(SENSOR_1);  // may not play sound
}
```

The last two types, `int *` and `const int *`, pass pointer arguments. Proper usage of pointer arguments requires that they be de-referenced.

```
void foo(int * p)
{
    *p = 4;
}

task main()
{
    int x = 2;
    int* y = &x; // y contains the address of x
    foo(y);     // x = 4
}
```

Functions must be invoked with the correct number (and type) of arguments. The example below shows several different legal and illegal calls to function `foo`:

```
void foo(int bar, const int baz)
{
```

```
        // do something here...
    }

    task main()
    {
        int x;        // declare variable x

        foo(1, 2);    // ok
        foo(x, 2);    // ok
        foo(2, x);    // error - 2nd argument not constant!
        foo(2);       // error - wrong number of arguments!
    }
}
```

NQC functions are always expanded as inline functions. This means that each call to a function results in another copy of the function's code being included in the program. Unless used judiciously, inline functions can lead to excessive code size.

2.2.3 Subroutines

Unlike inline functions, subroutines allow a single copy of some code to be shared between several different callers. This makes subroutines much more space efficient than inline functions, but due to some limitations in the LEGO bytecode interpreter, subroutines have some significant restrictions. First of all, subroutines cannot use any arguments. Second, a subroutine cannot call another subroutine. Last, the maximum number of subroutines is limited to 8 for the RCX, 4 for CyberMaster, 3 for Scout, and 32 for Spybotics. In addition, when using RCX 1.0 or CyberMaster, if the subroutine is called from multiple tasks then it cannot have any local variables or perform calculations that require temporary variables. These significant restrictions make subroutines less desirable than functions; therefore their use should be minimized to those situations where the resultant savings in code size is absolutely necessary. The syntax for a subroutine appears below:

```
sub name()
{
    // body of subroutine
}
```

2.2.4 Variables

All variables in NQC are of one of two types - specifically 16 bit signed integers or pointers to 16 bit signed integers. Variables are declared using the `int` keyword followed by a comma separated list of variable names (each with an optional '*' pointer indicator in front of the name) and terminated by a semicolon (';'). Optionally, an initial value for each variable may be specified using an equals sign ('=') after the variable name. Several examples appear below:

```
int x;      // declare x
int y,z;    // declare y and z
int *q, *p = &x; // declare ptrs q and p, p = address of x
int a=1,b;  // declare a and b, initialize a to 1
```

Global variables are declared at the program scope (outside any code block). Once declared, they may be used within all tasks, functions, and subroutines. Their scope begins at declaration and ends at the end of the program.

Local variables may be declared within tasks, functions, and sometimes within subroutines. Such variables are only accessible within the code block in which they are defined. Specifically, their scope begins with their declaration and ends at the end of their code block. In the case of local variables, a compound statement (a group of statements bracketed by { and }) is considered a block:

```
int x; // x is global

task main()
{
    int y; // y is local to task main
    x = y; // ok
    { // begin compound statement
        int z; // local z declared
        y = z; // ok
    }
    y = z; // error - z no longer in scope
}

task foo()
{
    x = 1; // ok
    y = 2; // error - y is not global
}
```

In many cases NQC must allocate one or more temporary variables for its own use. In some cases a temporary variable is used to hold an intermediate value during a calculation. In other cases it is used to hold a value as it is passed to a function. These temporary variables deplete the pool of variables available to the rest of the program. NQC attempts to be as efficient as possible with temporary variables (including reusing them when possible).

The RCX (and other targets) provide a number of storage locations which can be used to hold variables in an NQC program. There are two kinds of storage locations - global and local. When compiling a program, NQC assigns each variable to a specific storage location. Programmers for the most part can ignore the details of this assignment by following two basic rules:

- If a variable needs to be in a global location, declare it as a global variable.
- If a variable does not need to be a global variable, make it as local as possible.

This gives the compiler the most flexibility in assigning an actual storage location.

The number of global and local locations varies by target

Target	Global	Local
RCX (1.0)	32	0
CyberMaster	32	0
Scout	10	8
RCX2	32	16
Swan	32	16
Spybotics	32	4

2.2.5 Arrays

The RCX2, Swan, and Spybotics targets support arrays (the other targets do not have suitable support in firmware for arrays). Arrays are declared the same way as ordinary variables, but with the size of the array enclosed in brackets. The size must be a constant.

```
int my_array[3]; // declare an array with three elements
```

The elements of an array are identified by their position within the array (called an index). The first element has an index of 0, the second has index 1, etc. For example:

```
my_array[0] = 123; // set first element to 123
my_array[1] = my_array[2]; // copy third into second
```

Currently there are a number of limitations on how arrays can be used. These limitations will likely be removed in future versions of NQC:

- An array cannot be an argument to a function. An individual array element, however, can be passed to a function.
- Neither arrays nor their elements can be used with the increment (++) or decrement (--) operators.
- The initial values for an array's elements cannot be specified - an explicit assignment is required within the program itself to set the value of an element.

2.3 Statements

The body of a code block (task, function, or subroutine) is composed of statements. Statements are terminated with a semi-colon (;).

2.3.1 Variable Declaration

Variable declaration, as described in the previous section, is one type of statement. It declares a local variable (with optional initialization) for use within the code block. The syntax for a variable declaration is:

```
int variables;
```

where variables is a comma separated list of names with optional initial values and an optional pointer indicator:

```
[*]name[=expression]
```

Arrays of variables may also be declared (for the RCX2, Swan, and Spybotics only):

```
int array[size];
```

2.3.2 Assignment

Once declared, variables may be assigned the value of an expression:

```
variable assign_operator expression;
```

There are nine different assignment operators. The most basic operator, '=', simply assigns the value of the expression to the variable. The other operators modify the variable's value in some other way as shown in the table below

Operator	Action
=	Set variable to expression
+=	Add expression to variable
-=	Subtract expression from variable
*=	Multiple variable by expression
/=	Divide variable by expression
%=	Set variable to remainder after dividing by expression
&=	Bitwise AND expression into variable
=	Bitwise OR expression into variable
^=	Bitwise exclusive OR into variable
=	Set variable to absolute value of expression
+-=	Set variable to sign (-1,+1,0) of expression
>>=	Right shift variable by a constant amount
<<=	Left shift variable by a constant amount

Some examples:

```
x = 2;      // set x to 2
y = 7;      // set y to 7
x += y;     // x is 9, y is still 7
```

2.3.3 Control Structures

The simplest control structure is a compound statement. This is a list of statements enclosed within curly braces ('{' and '}'):

```
{
    x = 1;
    y = 2;
}
```

Although this may not seem very significant, it plays a crucial role in building more complicated control structures. Many control structures expect a single statement as their body. By using a compound statement, the same control structure can be used to control multiple statements.

The `if` statement evaluates a condition. If the condition is true it executes one statement (the consequence). An optional second statement (the alternative) is executed if the condition is false. The two syntaxes for an `if` statement is shown below.

```
if (condition) consequence
if (condition) consequence else alternative
```

Note that the condition is enclosed in parentheses. Examples are shown below. Note how a compound statement is used in the last example to allow two statements to be executed as the consequence of the condition.

```
if (x==1) y = 2;
if (x==1) y = 3; else y = 4;
if (x==1) { y = 1; z = 2; }
```

The `while` statement is used to construct a conditional loop. The condition is evaluated, and if true the body of the loop is executed, then the condition is tested again. This process continues until the condition becomes false (or a `break` statement is executed).

The syntax for a `while` loop appears below:

```
while (condition) body
```

It is very common to use a compound statement as the body of a loop:

```
while(x < 10)
{
    x = x+1;
    y = y*2;
}
```

A variant of the `while` loop is the `do-while` loop. Its syntax is:

```
do body while (condition)
```

The difference between a `while` loop and a `do-while` loop is that the `do-while` loop always executes the body at least once, whereas the `while` loop may not execute it at all.

Another kind of loop is the `for` loop:

```
for(stmt1 ; condition ; stmt2) body
```

A `for` loop always executes `stmt1`, then it repeatedly checks the condition and while it remains true executes the body followed by `stmt2`. The `for` loop is equivalent to:

```
stmt1;  
while(condition)  
{  
    body  
    stmt2;  
}
```

The `repeat` statement executes a loop a specified number of times:

```
repeat (expression) body
```

The expression determines how many times the body will be executed. Note that it is only evaluated a single time, then the body is repeated that number of times. This is different from both the `while` and `do-while` loops which evaluate their condition each time through the loop.

A `switch` statement can be used to execute one of several different blocks of code depending on the value of an expression. Each block of code is preceded by one or more `case` labels. Each case must be a constant and unique within the `switch` statement. The `switch` statement evaluates the expression then looks for a matching case label. It will then execute any statements following the matching case until either a `break` statement or the end of the `switch` is reached. A single `default` label may also be used - it will match any value not already appearing in a case label. Technically, a `switch` statement has the following syntax:

```
switch (expression) body
```

The `case` and `default` labels are not statements in themselves - they are *labels* that precede statements. Multiple labels can precede the same statement. These labels have the following syntax

```
case constant_expression :  
default :
```

A typical switch statement might look like this:

```
switch(x)  
{  
    case 1:  
        // do something when X is 1  
        break;  
    case 2:  
    case 3:  
        // do something else when x is 2 or 3  
        break;  
    default:  
        // do this when x is not 1, 2, or 3  
        break;  
}
```

The `goto` statement forces a program to jump to the specified location. Statements in a program can be labeled by preceding them with an identifier and a colon. A `goto` statement then specifies the label which the program should jump to. For example, this is how an infinite loop that increments a variable could be implemented using `goto`:

```
my_loop:  
    x++;  
    goto my_loop;
```

The `goto` statement should be used sparingly and cautiously. In almost every case, control structures such as `if`, `while`, and `switch` make a program much more readable and maintainable than using `goto`. Care should be taken to never use a `goto` to jump into or out of a `monitor` or `acquire` statement. This is because `monitor` and `acquire` have special code that normally gets executed upon entry and exit, and a `goto` will bypass that code – probably resulting in undesirable behavior.

NQC also defines the `until` macro which provides a convenient alternative to the `while` loop. The actual definition of `until` is:

```
#define until(c) while(!(c))
```

In other words, `until` will continue looping until the condition becomes true. It is most often used in conjunction with an empty body statement:

```
until(SENSOR_1 == 1); // wait for sensor to be pressed
```

2.3.4 Access Control and Events

The Scout, RCX2, Swan, and Spybotics support access control and event monitoring. Access control allows a task to request ownership of one or more resources. In NQC, access control is provided by the `acquire` statement, which has two forms:

```
acquire ( resources ) body
acquire ( resources ) body catch handler
```

where *resources* is a constant that specifies the resources to be acquired and *body* and *handler* are statements. The NQC API defines constants for individual resources which may be added together to request multiple resources at the same time. The behavior of the `acquire` statement is as follows: Ownership of the specified resources will be requested. If another task of higher priority already owns the resources, then the request will fail and execution will jump to the handler (if present). Otherwise, the request will succeed, and the body will begin to be executed. While executing the body, if another task of equal or higher priority requests any of the owned resources, then the original task will lose ownership. When ownership is lost, execution will jump to the handler (if present). Once the body has completed, the resources will be returned back to the system (so that lower priority tasks may acquire them), and execution will continue with the statement following the `acquire` statement. If a handler is not specified, then in both the case of a failed request, or a subsequent loss of ownership, control will pass to the statement following the `acquire` statement. For example, the following code acquires a resource for 10 seconds, playing a sound if it cannot complete successfully:

```
acquire(ACQUIRE_OUT_A)
{
    Wait(1000);
}
catch
{
    PlaySound(SOUND_UP);
}
```

Event monitoring is implemented with the `monitor` statement, which has a syntax very similar to `acquire`:

```
monitor ( events ) body
monitor ( events ) body handler_list
```

Where `handler_list` is one or more handlers of the form

```
catch ( catch_events ) handler
```

The last handler in a handler list can omit the event specification:

```
catch handler
```

Events is a constant that determines which events should be monitored. For the Scout, events are predefined, so there are constants such as `EVENT_1_PRESSED` which can be used to specify events. With RCX2, Swan, and Spybotics, the meaning of each event is configured by the programmer. There are 16 events (numbers 0 to 15). In order to specify an event in a monitor statement, the event number must be converted to an event mask using the `EVENT_MASK()` macro. The Scout event constants or event masks may be added together to specify multiple events. Multiple masks can be combined using bitwise OR.

The monitor statement will execute the body while monitoring the specified events. If any of the events occur, execution will jump to the first handler for that event (a handler without an event specification handles any event). If no event handler exists for the event, then control will continue at the statement following the monitor statement. The following example waits for 10 seconds while monitoring events 2, 3, and 4 for RCX2:

```
monitor( EVENT_MASK(2) | EVENT_MASK(3) | EVENT_MASK(4) )
{
    Wait(1000);
}
catch ( EVENT_MASK(4) )
{
    PlaySound(SOUND_DOWN); // event 4 happened
}
catch
{
    PlaySound(SOUND_UP); // event 2 or 3 happened
}
```

Note that the acquire and monitor statements are only supported for targets that implement access control and event monitoring - specifically the Scout, RCX2, Swan, and Spybotics.

2.3.5 Other Statements

A function (or subroutine) call is a statement of the form:

```
name(arguments);
```

The arguments list is a comma separated list of expressions. The number and type of arguments supplied must match the definition of the function itself.

Tasks may be started or stopped with the following statements:

```
start task_name;  
stop task_name;
```

Within loops (such as a `while` loop) the `break` statement can be used to exit the loop and the `continue` statement can be used to skip to the top of the next iteration of the loop. The `break` statement can also be used to exit a `switch` statement.

```
break;  
continue;
```

It is possible to cause a function to return before it reaches the end of its code using the `return` statement.

```
return;
```

Any expression is also a legal statement when terminated by a semicolon. It is rare to use such a statement since the value of the expression would then be discarded. The one notable exception is expressions involving the increment (`++`) or decrement (`--`) operators.

```
x++;
```

The empty statement (just a bare semicolon) is also a legal statement.

2.4 Expressions

Earlier versions of NQC made a distinction between expressions and conditions. As of version 2.3, this distinction was eliminated: everything is an expression, and there are now conditional operators for expressions. This is similar to how C/C++ treats conditional operations.

Values are the most primitive type of expressions. More complicated expressions are formed from values using various operators. The NQC language only has two built in kinds of values: numerical constants and variables. The RCX API defines other values corresponding to various RCX features such as sensors and timers.

Numerical constants in the RCX are represented as 16 bit signed integers. NQC internally uses 32 bit signed math for constant expression evaluation, then reduces to 16 bits when generating RCX code. Numeric constants can be written as either decimal (e.g. 123) or hexadecimal (e.g. 0xABC). Presently, there is very little range checking on constants, so using a value larger than expected may have unusual effects.

Two special values are predefined: `true` and `false`. The value of `false` is zero, while the value of `true` is only guaranteed to be non-zero. The same values hold for relational operators (e.g. `<`): when the relation is false, the value is 0, otherwise the value is non-zero.

Values may be combined using operators. Several of the operators may only be used in evaluating constant expressions, which means that their operands must either be constants, or expressions involving nothing but constants. The operators are listed here in order of precedence (highest to lowest).

Operator	Description	Associativity	Restriction	Example
<code>abs()</code>	Absolute value	n/a		<code>abs(x)</code>
<code>sign()</code>	Sign of operand	n/a		<code>sign(x)</code>
<code>++, --</code>	Increment, decrement	left	variables only	<code>x++</code> or <code>++x</code>
<code>-</code>	Unary minus	right		<code>-x</code>
<code>~</code>	Bitwise negation (unary)	right	constant only	<code>~123</code>
<code>!</code>	Logical negation	right		<code>!x</code>
<code>*, /, %</code>	Multiplication, division, modulo	left		<code>x * y</code>
<code>+, -</code>	Addition, subtraction	left		<code>x + y</code>
<code><<, >></code>	Left and right shift	left	shift amount must constant	<code>x << 4</code>

<, >, <=, >=	relational operators	left		x < y
==, !=	equal to, not equal to	left		x == 1
&	Bitwise AND	left		x & y
^	Bitwise XOR	left		x ^ y
	Bitwise OR	left		x y
&&	Logical AND	left		x && y
	Logical OR	left		x y
?:	conditional value	n/a		x==1 ? y : z

Where needed, parentheses may be used to change the order of evaluation:

```
x = 2 + 3 * 4;    // set x to 14
y = (2 + 3) * 4; // set y to 20
```

2.4.1 Conditions

Conditions are generally formed by comparing two expressions. There are also two constant conditions - `true` and `false` - which always evaluate to true or false respectively. A condition may be negated with the negation operator, or two conditions combined with the AND and OR operators. The table below summarizes the different types of conditions.

Condition	Meaning
True	always true
False	always false
Expr	true if expr is not equal to 0
expr1 == expr2	true if expr1 equals expr2
expr1 != expr2	true if expr1 is not equal to expr2
expr1 < expr2	true if one expr1 is less than expr2
expr1 <= expr2	true if expr1 is less than or equal to expr2

<code>expr1 > expr2</code>	true if expr1 is greater than expr2
<code>expr1 >= expr2</code>	true if expr1 is greater than or equal to expr2
<code>! condition</code>	logical negation of a condition - true if condition is false
<code>cond1 && cond2</code>	logical AND of two conditions (true if and only if both conditions are true)
<code>cond1 cond2</code>	logical OR of two conditions (true if and only if at least one of the conditions are true)

2.5 The Preprocessor

The preprocessor implements the following directives: `#include`, `#define`, `#ifdef`, `#ifndef`, `#if`, `#elif`, `#else`, `#endif`, `#undef`. Its implementation is fairly close to a standard C preprocessor, so most things that work in a generic C preprocessor should have the expected effect in NQC. Significant deviations are listed below.

2.5.1 `#include`

The `#include` command works as expected, with the caveat that the filename must be enclosed in double quotes. There is no notion of a system include path, so enclosing a filename in angle brackets is forbidden.

```
#include "foo.nqh" // ok
#include <foo.nqh> // error!
```

2.5.2 `#define`

The `#define` command is used for simple macro substitution. Redefinition of a macro is an error (unlike in C where it is a warning). Macros are normally terminated by the end of the line, but the newline may be escaped with the backslash (`\`) to allow multi-line macros:

```
#define foo(x) do { bar(x); \
                    baz(x); } while(false)
```

The `#undef` directive may be used to remove a macro's definition.

2.5.3 Conditional Compilation

Conditional compilation works similar to the C preprocessor. The following preprocessor directives may be used:

```
#if condition
#ifdef symbol
#ifndef symbol
#else
#elif condition
#endif
```

Conditions in `#if` directives use the same operators and precedence as in C. The `defined()` operator is supported.

2.5.4 Program Initialization

The compiler will insert a call to a special initialization function, `_init`, at the start of a program. This default function is part of the RCX API and sets all three outputs to full power in the forward direction (but still turned off). The initialization function can be disabled using the `#pragma noint` directive:

```
#pragma noint // don't do any program initialization
```

The default initialization function can be replaced with a different function using the `#pragma init` directive.

```
#pragma init function // use custom initialization
```

2.5.5 Reserving Storage

The NQC compiler automatically assigns variables to storage locations. However, sometimes it is necessary to prevent the compiler from using certain storage locations.

This can be done with the `#pragma reserve` directive:

```
#pragma reserve start
#pragma reserve start end
```

This directive forces the compiler to ignore one or more storage locations during variable assignment. Start and end must be numbers that refer to valid storage locations. If only a

start is provided, then that single location is reserved. If start and end are both specified, then the range of locations from start to end (inclusive) are reserved. The most common use of this directive is to reserve locations 0, 1, and/or 2 when using counters for RCX2, Swan, and Spybotics. This is because the RCX2, Swan, and Spybotics counters are overlapped with storage locations 0, 1, and 2. For example, if all three counters were going to be used:

```
#pragma reserve 0 2
```

3 NQC API

The NQC API defines a set of constants, functions, values, and macros that provide access to various capabilities of the target such as sensors, outputs, timers, and communication. Some features are only available on certain targets. Where appropriate, a section's title will indicate which targets it applies to. The RCX2 and Swan are a superset of RCX features, so if RCX is listed, then the feature works with the original firmware, the 2.0 firmware, and the Swan firmware. If RCX2 is listed, then the feature only applies to the 2.0 firmware and the Swan firmware. If Swan is listed alone, then the feature only applies to the Swan firmware. CyberMaster, Scout, and Spybotics are indicated by CM, Scout, and Spy respectively.

The API consists of functions, values, and constants. A function is something that can be called as a statement. Typically it takes some action or configures some parameter. Values represent some parameter or quantity and can be used in expressions. Constants are symbolic names for values that have special meanings for the target. Often, a set of constants will be used in conjunction with a function. For example, the `PlaySound` function takes a single argument which determines which sound is to be played. Constants, such as `SOUND_UP`, are defined for each sound.

3.1 Sensors

There are three sensors, which internally are numbered 0, 1, and 2. This is potentially confusing since they are externally labeled on the RCX as sensors 1, 2, and 3. To help mitigate this confusion, the sensor names `SENSOR_1`, `SENSOR_2`, and `SENSOR_3` have been defined. These sensor names may be used in any function that requires a sensor as an argument. Furthermore, the names may also be used whenever a program wishes to read the current value of the sensor:

```
x = SENSOR_1; // read sensor and store value in x
```

3.1.1 Types and Modes

RCX, CM, Spy

The sensor ports on the RCX are capable of interfacing to a variety of different sensors (other targets don't support configurable sensor types). It is up to the program to tell the RCX what kind of sensor is attached to each port. A sensor's type may be configured by calling `SetSensorType`. . There are four sensor types, each corresponding to a specific LEGO sensor. A fifth type (`SENSOR_TYPE_NONE`) can be used for reading the raw values of generic passive sensors. In general, a program should configure the type to match the actual sensor. If a sensor port is configured as the wrong type, the RCX may not be able to read it accurately.

Sensor Type	Meaning
<code>SENSOR_TYPE_NONE</code>	generic passive sensor
<code>SENSOR_TYPE_TOUCH</code>	a touch sensor
<code>SENSOR_TYPE_TEMPERATURE</code>	a temperature sensor
<code>SENSOR_TYPE_LIGHT</code>	a light sensor
<code>SENSOR_TYPE_ROTATION</code>	a rotation sensor

The RCX, CyberMaster, and Spybotics allow a sensor to be configured in different modes. The sensor mode determines how a sensor's raw value is processed. Some modes only make sense for certain types of sensors, for example `SENSOR_MODE_ROTATION` is useful only with rotation sensors. The sensor mode can be set by calling `SetSensorMode`. The possible modes are shown below. Note that since CyberMaster does not support temperature or rotation sensors, the last three modes are restricted to the RCX only. Spybotics is even more restrictive, allowing only raw, boolean, and percentage modes.

Sensor Mode	Meaning
<code>SENSOR_MODE_RAW</code>	raw value from 0 to 1023
<code>SENSOR_MODE_BOOL</code>	boolean value (0 or 1)
<code>SENSOR_MODE_EDGE</code>	counts number of boolean transitions
<code>SENSOR_MODE_PULSE</code>	counts number of boolean periods
<code>SENSOR_MODE_PERCENT</code>	value from 0 to 100
<code>SENSOR_MODE_FAHRENHEIT</code>	degrees F - RCX only

NQC Programmer's Guide

SENSOR_MODE_CELSIUS	degrees C - RCX only
SENSOR_MODE_ROTATION	rotation (16 ticks per revolution) - RCX only

When using the RCX, it is common to set both the type and mode at the same time. The SetSensor function makes this process a little easier by providing a single function to call and a set of standard type/mode combinations.

Sensor Configuration	Type	Mode
SENSOR_TOUCH	SENSOR_TYPE_TOUCH	SENSOR_MODE_BOOL
SENSOR_LIGHT	SENSOR_TYPE_LIGHT	SENSOR_MODE_PERCENT
SENSOR_ROTATION	SENSOR_TYPE_ROTATION	SENSOR_MODE_ROTATION
SENSOR_CELSIUS	SENSOR_TYPE_TEMPERATURE	SENSOR_MODE_CELSIUS
SENSOR_FAHRENHEIT	SENSOR_TYPE_TEMPERATURE	SENSOR_MODE_FAHRENHEIT
SENSOR_PULSE	SENSOR_TYPE_TOUCH	SENSOR_MODE_PULSE
SENSOR_EDGE	SENSOR_TYPE_TOUCH	SENSOR_MODE_EDGE

The RCX provides a boolean conversion for all sensors - not just touch sensors. This boolean conversion is normally based on preset thresholds for the raw value. A "low" value (less than 460) is a boolean value of 1. A high value (greater than 562) is a boolean value of 0. This conversion can be modified: a *slope value* between 0 and 31 may be added to a sensor's mode when calling SetSensorMode. If the sensor's value changes more than the slope value during a certain time (3ms), then the sensor's boolean state will change. This allows the boolean state to reflect rapid changes in the raw value. A rapid increase will result in a boolean value of 0, a rapid decrease is a boolean value of 1.

Even when a sensor is configured for some other mode (i.e. SENSOR_MODE_PERCENT), the boolean conversion will still be carried out.

SetSensor(sensor, configuration)

Function - RCX

Set the type and mode of the given sensor to the specified configuration, which must be a special constant containing both type and mode information.

```
SetSensor(SENSOR_1, SENSOR_TOUCH);
```

SetSensorType(sensor, type)

Function - RCX

Set a sensor's type, which must be one of the predefined sensor type constants.

```
SetSensorType(SENSOR_1, SENSOR_TYPE_TOUCH);
```

SetSensorMode(sensor, mode)

Function - RCX, CM, Spy

Set a sensor's mode, which should be one of the predefined sensor mode constants. A slope parameter for boolean conversion, if desired, may be added to the mode (RCX only).

```
SetSensorMode(SENSOR_1, SENSOR_MODE_RAW); // raw mode
SetSensorMode(SENSOR_1, SENSOR_MODE_RAW + 10); // slope 10
```

ClearSensor(sensor)

Function - All

Clear the value of a sensor - only affects sensors that are configured to measure a cumulative quantity such as rotation or a pulse count.

```
ClearSensor(SENSOR_1);
```

3.1.2 Sensor Information

There are a number of values that can be inspected for each sensor. For all of these values the sensor must be specified by its sensor number (0, 1, or 2), and not a sensor name (e.g. SENSOR_1).

SensorValue(n)

Value - All

Returns the processed sensor reading for sensor n, where n is 0, 1, or 2. This is the same value that is returned by the sensor names (e.g. SENSOR_1).

```
x = SensorValue(0); // read sensor 1
```

SensorType(n)

Value - All

Returns the configured type of sensor n, which must be 0, 1, or 2. Only the RCX has configurable sensors types, other targets will always return the pre-configured type of the sensor.

```
x = SensorType(0);
```

SensorMode(n)

Value - RCX, CM, Spy

Returns the current sensor mode for sensor n, which must be 0, 1, or 2.

```
x = SensorMode(0);
```

SensorValueBool(n)

Value - RCX

Returns the boolean value of sensor n, which must be 0, 1, or 2. Boolean conversion is either done based on preset cutoffs, or a slope parameter specified by calling `SetSensorMode`.

```
x = SensorValueBool(0);
```

SensorValueRaw(n)

Value - RCX, Scout, Spy

Returns the raw value of sensor n, which must be 0, 1, or 2. Raw values may range from 0 to 1023 (RCX, Spy) or 0 to 255 (Scout).

```
x = SensorValueRaw(0);
```

3.1.3 Scout Light Sensor

Scout

On the Scout, `SENSOR_3` refers to the built-in light sensor. Reading the light sensor's value (with `SENSOR_3`) will return one of three levels: 0 (dark), 1 (normal), or 2 (bright). The sensor's raw value can be read with `SensorValueRaw(SENSOR_3)`, but bear in mind that brighter light will result in a *lower* raw value. The conversion of the sensor's raw value (between 0 and 1023) to one of the three levels depends on three parameters: *lower limit*, *upper limit*, and *hysteresis*. The lower limit is the smallest (brightest) raw value that is still considered *normal*. Values below the lower limit will be considered *bright*. The upper limit is the largest (darkest) raw value that is considered *normal*. Values about this limit are considered *dark*.

Hysteresis can be used to prevent the level from changing when the raw value hovers near one of the limits. This is accomplished by making it a little harder to leave the dark and bright states than it is to enter them. Specifically, the limit for moving from normal to bright will be a little lower than the limit for moving from bright back to normal. The

difference between these two limits is the amount of hysteresis. A symmetrical case holds for the transition between normal and dark.

SetSensorLowerLimit(value)

Function - Scout

Set the light sensor's lower limit. Value may be any expression.

```
SetSensorLowerLimit(100);
```

SetSensorUpperLimit(value)

Function - Scout

Set the light sensor's upper limit. Value may be any expression.

```
SetSensorUpperLimit(900);
```

SetSensorHysteresis (value)

Function - Scout

Set the light sensor's hysteresis. Value may be any expression.

```
SetSensorHysteresis(20);
```

CalibrateSensor()

Function - Scout

Reads the current value of the light sensor, then sets the upper and lower limits to 12.5% above and below the current reading, and sets the hysteresis to 3.12% of the reading.

```
CalibrateSensor();
```

3.1.4 Spybotics Sensors

Spy

Spybotics uses built-in sensors instead of externally connected ones. The touch sensor on the front of the Spybotics brick is `SENSOR_1`. It is normally configured in percentage mode, so it has a value of 0 when not pressed, and a value of 100 when pressed.

`SENSOR_2` is the light sensor (the connector on the back of the brick that is used to communicate with a computer). It is normally configured in percentage mode, where higher numbers indicate brighter light.

3.2 Outputs

3.2.1 Primitive Calls

All of the functions dealing with outputs take a set of outputs as their first argument. This set must be a constant. The names `OUT_A`, `OUT_B`, and `OUT_C` are used to identify the three outputs. Multiple outputs can be combined by adding individual outputs together. For example, use `OUT_A+OUT_B` to specify outputs A and B together. The set of outputs must always be a compile time constant (it cannot be a variable).

Each output has three different attributes: mode, direction, and power level. The mode can be set by calling `SetOutput(outputs, mode)`. The mode parameter should be one of the following constants:

Output Mode	Meaning
<code>OUT_OFF</code>	output is off (motor is prevented from turning)
<code>OUT_ON</code>	output is on (motor will be powered)
<code>OUT_FLOAT</code>	motor can "coast"

The other two attributes, direction and power level, may be set at any time, but only have an effect when the output is on. The direction is set with the `SetDirection(outputs, direction)` command. The direction parameter should be one of the following constants:

Direction	Meaning
<code>OUT_FWD</code>	Set to forward direction
<code>OUT_REV</code>	Set to reverse direction
<code>OUT_TOGGLE</code>	Switch direction to the opposite of what it is presently

The power level can range 0 (lowest) to 7 (highest). The names `OUT_LOW`, `OUT_HALF`, and `OUT_FULL` are defined for use in setting power level. The level is set using the `SetPower(outputs, power)` function.

By default, all three motors are set to full power and the forward direction (but still turned off) when a program starts.

SetOutput(outputs, mode)

Function - All

Set the outputs to the specified mode. Outputs is one or more of OUT_A, OUT_B, and OUT_C. Mode must be OUT_ON, OUT_OFF, or OUT_FLOAT.

```
SetOutput(OUT_A + OUT_B, OUT_ON); // turn A and B on
```

SetDirection(outputs, direction)

Function - All

Set the outputs to the specified direction. Outputs is one or more of OUT_A, OUT_B, and OUT_C. Direction must be OUT_FWD, OUT_REV, or OUT_TOGGLE.

```
SetDirection(OUT_A, OUT_REV); // make A turn backwards
```

SetPower(outputs, power)

Function - All

Sets the power level of the specified outputs. Power may be an expression, but should result in a value between 0 and 7. The constants OUT_LOW, OUT_HALF, and OUT_FULL may also be used.

```
SetPower(OUT_A, OUT_FULL); // A full power
SetPower(OUT_B, x);
```

OutputStatus(n)

Value - All

Returns the current output setting for motor n. Note that n must be 0, 1, or 2 - not OUT_A, OUT_B, or OUT_C.

```
x = OutputStatus(0); // status of OUT_A
```

3.2.2 Convenience Calls

Since control of outputs is such a common feature of programs, a number of convenience functions are provided that make it easier to work with the outputs. It should be noted that these commands do not provide any new functionality above the SetOutput and SetDirection commands. They are merely convenient ways to make programs more concise.

On(outputs)

Function - All

Turn specified outputs on. Outputs is one or more of OUT_A, OUT_B, and OUT_C added together.

```
On(OUT_A + OUT_C); // turn on outputs A and C
```

Off(outputs)

Function - All

Turn specified outputs off. Outputs is one or more of OUT_A, OUT_B, and OUT_C added together.

```
Off(OUT_A); // turn off output A
```

Float(outputs)

Function - All

Make outputs float. Outputs is one or more of OUT_A, OUT_B, and OUT_C added together.

```
Float(OUT_A); // float output A
```

Fwd(outputs)

Function - All

Set outputs to forward direction. Outputs is one or more of OUT_A, OUT_B, and OUT_C added together.

```
Fwd(OUT_A);
```

Rev(outputs)

Function - All

Set outputs to reverse direction. Outputs is one or more of OUT_A, OUT_B, and OUT_C added together.

```
Rev(OUT_A);
```

Toggle(outputs)

Function - All

Flip the direction of the outputs. Outputs is one or more of OUT_A, OUT_B, and OUT_C added together.

```
Toggle(OUT_A);
```

OnFwd(outputs)

Function - All

Set outputs to forward direction and turn them on. Outputs is one or more of OUT_A, OUT_B, and OUT_C added together.

```
OnFwd(OUT_A);
```

OnRev(outputs)

Function - All

Set outputs to reverse direction and turn them on. Outputs is one or more of OUT_A, OUT_B, and OUT_C added together.

```
OnRev(OUT_A);
```

OnFor(outputs, time)

Function - All

Turn outputs on for a specified amount of time, then turn them off. Outputs is one or more of OUT_A, OUT_B, and OUT_C added together. Time is measures in 10ms increments (one second = 100) and may be any expression.

```
OnFor(OUT_A, x);
```

3.2.3 Global Control

RCX2, Scout, Spy

SetGlobalOutput(outputs, mode)

Function - RCX2, Scout, Spy

Disable or re-enable outputs depending on the mode parameter. If mode is OUT_OFF, then the outputs will be turned off and disabled. While disabled any subsequent calls to SetOutput() (including convenience functions such as On()) will be ignored. Using a mode of OUT_FLOAT will put the outputs in float mode before disabling them. Outputs can be re-enabled by calling SetGlobalOutput() with a mode of OUT_ON. Note that enabling an output doesn't immediately turn it on - it just allows future calls to SetOutput() to take effect.

```
SetGlobalOutput(OUT_A, OUT_OFF); // disable output A
SetGlobalOutput(OUT_A, OUT_ON); // enable output A
```

SetGlobalDirection(outputs, direction) **Function - RCX2, Scout, Spy**

Reverses or restores the directions of outputs. The direction parameter should be OUT_FWD, OUT_REV, or OUT_TOGGLE. Normal behavior is a global direction of OUT_FWD. When the global direction is OUT_REV, then the actual output direction will be the opposite of whatever the regular output calls request. Calling SetGlobalDirection() with OUT_TOGGLE will switch between normal and opposite behavior.

```
SetGlobalDirection(OUT_A, OUT_REV); // opposite direction
SetGlobalDirection(OUT_A, OUT_FWD); // normal direction
```

SetMaxPower(outputs, power) **Function - RCX2, Scout, Spy**

Sets the maximum power level allowed for the outputs. The power level may be a variable, but should have a value between OUT_LOW and OUT_FULLL.

```
SetMaxPower(OUT_A, OUT_HALF);
```

GlobalOutputStatus(n) **Value - RCX2, Scout, Spy**

Returns the current global output setting for motor n. Note that n must be 0, 1, or 2 - not OUT_A, OUT_B, or OUT_C.

```
x = GlobalOutputStatus(0); // global status of OUT_A
```

EnableOutput(outputs) **Function - RCX2, Scout, Spy**

A helper function for enabling the specified outputs. Use OUT_A, OUT_B, or OUT_C.

```
EnableOutput(OUT_A+OUT_B); // enable OUT_A and OUT_B
```

This is the same as using SetGlobalOutput with the OUT_ON mode.

DisableOutput(outputs) **Function - RCX2, Scout, Spy**

A helper function for disabling the specified outputs. Use OUT_A, OUT_B, or OUT_C.

```
DisableOutput(OUT_A+OUT_B); // disable OUT_A and OUT_B
```

This is the same as using `SetGlobalOutput` with the `OUT_OFF` mode.

InvertOutput(outputs)

Function - RCX2, Scout, Spy

A helper function for inverting the direction of the specified outputs. Use `OUT_A`, `OUT_B`, or `OUT_C`.

```
InvertOutput(OUT_A+OUT_B); // reverse dir OUT_A and OUT_B
```

This is the same as using `SetGlobalDirection` with the `OUT_REV` direction.

ObvertOutput(outputs)

Function - RCX2, Scout, Spy

A helper function for returning the direction of the specified outputs to forward. Use `OUT_A`, `OUT_B`, or `OUT_C`.

```
ObvertOutput(OUT_A+OUT_B); // normal dir OUT_A and OUT_B
```

This is the same as using `SetGlobalDirection` with the `OUT_FWD` direction.

3.2.4 Spybotics Outputs

Spybotics has two built-in motors. `OUT_A` refers to the right motor, and `OUT_B` is for the left motor. `OUT_C` will send VLL commands out the rear LED (the one used for communication with a computer). This allows a VLL device, such as a Micro-Scout, to be used as a third motor for Spybotics. The same LED may be controlled using the `SendVLL()` and `SetLight()` functions.

3.3 Sound

PlaySound(sound)

Function - All

Plays one of the 6 preset RCX sounds. The sound argument must be a constant (except on Spybotics, which allows a variable to be used). The following constants are pre-defined for use with `PlaySound`: `SOUND_CLICK`, `SOUND_DOUBLE_BEEP`, `SOUND_DOWN`, `SOUND_UP`, `SOUND_LOW_BEEP`, `SOUND_FAST_UP`.

```
PlaySound(SOUND_CLICK);
```

The Spybotics brick has additional sound support via this function. It has 64 preset sounds in ROM (numbered 0-63). The additional 58 constants defined for these sounds are:

Spybot Sound Effect Constants

```
SOUND_SHOCKED, SOUND_FIRE_LASER, SOUND_FIRE_ELECTRONET,  
SOUND_FIRE_SPINNER, SOUND_HIT_BY_LASER,  
SOUND_HIT_BY_ELECTRONET, SOUND_HIT_BY_SPINNER, SOUND_TAG,  
SOUND_CRASH, SOUND_FIGHT, SOUND_GOT_IT,  
SOUND_GENERAL_ALERT, SOUND_OUT_OF_ENERGY_ALERT,  
SOUND_LOW_ENERGY_ALERT, SOUND_SCORE_ALERT,  
SOUND_TIME_ALERT, SOUND_PROXIMITY_ALERT,  
SOUND_DANGER_ALERT, SOUND_BOMB_ALERT,  
SOUND_FINAL_COUNTDOWN, SOUND_TICK_TOCK, SOUND_GOTO,  
SOUND_SCAN, SOUND_POINT_TO, SOUND_ACTIVATE_SHIELDS,  
SOUND_ACTIVATE_REFLECT, SOUND_ACTIVATE_CLOAK,  
SOUND_ACTIVATE_FLASH_BLIND, SOUND_MAGNET,  
SOUND_QUAD_DAMAGE, SOUND_REPULSE, SOUND_TURBO,  
SOUND_FREEZE, SOUND_SLOW, SOUND_REVERSE, SOUND_DIZZY,  
SOUND_BOOST, SOUND_DEACTIVATE_SHIELDS,  
SOUND_DEACTIVATE_REFLECT, SOUND_DEACTIVATE_CLOAK,  
SOUND_REFLECT, SOUND_EXPLOSION, SOUND_BIG_EXPLOSION,  
SOUND_PLACE_BOMB, SOUND_HIT_BY_WIND, SOUND_OUCH,  
SOUND_GEIGER, SOUND_WHISTLE, SOUND_IM_IT, SOUND_HELP,  
SOUND_SIREN, SOUND_BURNT, SOUND_GRINDED, SOUND_SMACKED,  
SOUND_TRILL_UP, SOUND_TRILL_DOWN, SOUND_YELL, SOUND_WHISPER
```

A special constant, SOUND_NONE, is also defined for the Spybotics target to indicate that no sound should be played.

PlayTone(frequency, duration)

Function - All

Plays a single tone of the specified frequency and duration. The frequency is in Hz and can be a variable for RCX2, Scout, and Spybotics, but has to be constant for RCX and CyberMaster. The duration is in 100ths of a second and must be a constant.

```
PlayTone(440, 50); // Play 'A' for one half second
```

MuteSound()

Function - RCX2, Scout, Spy

Stops all sounds and tones from being played.

```
MuteSound();
```

UnmuteSound()

Function - RCX2, Scout, Spy

Restores normal operation of sounds and tones.

```
UnmuteSound();
```

ClearSound()

Function - RCX2, Spy

Removes any pending sounds from the sound buffer.

```
ClearSound();
```

SelectSounds(group)

Function - Scout

Selects which group of system sounds should be used. The group must be a constant.

```
SelectSounds(0);
```

3.4 LCD Display

RCX

The RCX has seven different display modes as shown below. The RCX defaults to DISPLAY_WATCH.

Mode	LCD Contents
DISPLAY_WATCH	show the system "watch"
DISPLAY_SENSOR_1	show value of sensor 1
DISPLAY_SENSOR_2	show value of sensor 2
DISPLAY_SENSOR_3	show value of sensor 3
DISPLAY_OUT_A	show setting for output A
DISPLAY_OUT_B	show setting for output B
DISPLAY_OUT_C	show setting for output C

The RCX2 adds an eighth display mode - DISPLAY_USER. User display mode continuously reads a source value and updates the display. It can optionally display a decimal point at any position within the number. This allows the display to give the illusion of working with fractions even though all values are stored internally as integers. For example, the following call will set the user display to show the value 1234 with two digits appearing after the decimal point, resulting in "12.34" appearing on the LCD.

```
SetUserDisplay(1234, 2);
```

The following short program illustrates the update of the user display:

```
task main()  
{
```

```
    ClearTimer(0);
    SetUserDisplay(Timer(0), 0);
    until(false);
}
```

Because the user display mode continuously updates the LCD, there are certain restrictions on the source value. If a variable is used it must be assigned to a global storage location. The best way to ensure this is to make the variable a global one. There can also be some strange side effects. For example, if a variable is being displayed and later used as the target of a calculation, it is possible for the display to show some intermediate results of the calculation:

```
int x;
task main()
{
    SetUserDisplay(x, 0);
    while(true)
    {
        // display may briefly show 1!
        x = 1 + Timer(0);
    }
}
```

SelectDisplay(mode)

Function - RCX

Select a display mode.

```
SelectDisplay(DISPLAY_SENSOR_1); // view sensor 1
```

SetUserDisplay(value, precision)

Function - RCX2

Set the LCD display to continuously monitor the specified value. Precision specifies the number of digits to the right of the decimal point. A precision of zero shows no decimal point.

```
SetUserDisplay(Timer(0), 0); // view timer 0
```

3.5 Communication

3.5.1 Messages

RCX, Scout

The RCX and Scout can send and receive simple messages using IR. A message can have a value from 0 to 255, but the use of message 0 is discouraged. The most recently

received message is remembered and can be accessed as `Message()`. If no message has been received, `Message()` will return 0. Note that due to the nature of IR communication, receiving is disabled while a message is being transmitted.

ClearMessage()

Function - RCX, Scout

Clear the message buffer. This facilitates detection of the next received message since the program can then wait for `Message()` to become non-zero:

```
ClearMessage(); // clear out the received message
until(Message() > 0); // wait for next message
```

SendMessage(message)

Function - RCX, Scout

Send an IR message. `Message` may be any expression, but the RCX can only send messages with a value between 0 and 255, so only the lowest 8 bits of the argument are used.

```
SendMessage(3); // send message 3
SendMessage(259); // another way to send message 3
```

SetTxPower(power)

Function - RCX, Scout

Set the power level for IR transmission. Power should be one of the constants `TX_POWER_LO` or `TX_POWER_HI`.

MessageParam()

Value - Swan

Read the message parameter. The Swan firmware supports a 2 byte message parameter in addition to the single byte supported by the RCX firmware.

```
x = MessageParam(); // read the rcvd msg param value
```

SendMessageWithParam(const int &m, const int &p) **Function - Swan**

Send an IR message with an additional parameter. The first parameter is restricted a single byte while the second parameter can be two bytes.

```
SendMessageWithParam(3, 1024);
```

SetMessageByteParam(const int m, const int p) Function - Swan

Set the IR message and its parameter using constants. The parameter must be a single byte value.

```
SetMessageByteParam(3, 43);
```

SetMessageWordParam(const int m, const int p) Function - Swan

Set the IR message and its parameter using constants. The parameter can be 2 bytes.

```
SetMessageWordParam(3, 1024);
```

SetMessageVariableParam(const int &m, const int &p) Function - Swan

Set the IR message and its parameter using variables. The parameter can be 2 bytes.

```
SetMessageVariableParam(x, y);
```

3.5.2Serial

RCX2, Spy

The RCX2 and Spybotics can transmit serial data out the IR port. Prior to transmitting any data, the communication and packet settings must be specified. Then, for each transmission, data should be placed in the transmit buffer, then sent using the `SendSerial()` function.

For the RCX2 the communication settings are set with `SetSerialComm`. This determines how bits are sent over IR. Possible values are shown below.

Option	Effect
SERIAL_COMM_DEFAULT	default settings
SERIAL_COMM_4800	4800 baud
SERIAL_COMM_DUTY25	25% duty cycle
SERIAL_COMM_76KHZ	76kHz carrier

The default is to send data at 2400 baud using a 50% duty cycle on a 38kHz carrier. To specify multiple options (such as 4800 baud with 25% duty cycle), combine the individual options using bitwise or (`SERIAL_COMM_4800 | SERIAL_COMM_DUTY25`).

The RCX2 also allows you to set the packet settings with `SetSerialPacket`. This controls how bytes are assembled into packets. Possible values are shown below.

Option	Effect
<code>SERIAL_PACKET_DEFAULT</code>	no packet format - just data bytes
<code>SERIAL_PACKET_PREAMBLE</code>	send a packet preamble
<code>SERIAL_PACKET_NEGATED</code>	follow each byte with its complement
<code>SERIAL_PACKET_CHECKSUM</code>	include a checksum for each packet
<code>SERIAL_PACKET_RCX</code>	standard RCX format (preamble, negated data, and checksum)

Note that negated packets always include a checksum, so the `SERIAL_PACKET_CHECKSUM` option is only meaningful when `SERIAL_PACKET_NEGATED` is not specified. Likewise the preamble, negated, and checksum settings are implied by `SERIAL_PACKET_RCX`.

The transmit buffer can hold up to 16 data bytes. These bytes may be set using `SetSerialData`, then transmitted by calling `SendSerial`. For example, the following code sends two bytes (0x12 and 0x34) out the serial port:

```
SetSerialComm(SERIAL_COMM_DEFAULT);  
SetSerialPacket(SERIAL_PACKET_DEFAULT);  
SetSerialData(0, 0x12);  
SetSerialData(1, 0x34);  
SendSerial(0, 2);
```

Spybotics uses a different mechanism for configuring the serial transmission parameters. Use `SetSerialType` to specify the transmission type with the constants described in the following table.

Option	Effect
<code>SERIAL_TYPE_SPYBOT</code>	Spybotics type
<code>SERIAL_TYPE_RCX</code>	RCX type
<code>SERIAL_TYPE_RC</code>	RC type
<code>SERIAL_TYPE_USER</code>	User-defined type

Use `SetSerialBaud` to specify the baud rate with the constants described in the following table.

Option	Effect
<code>SERIAL_BAUD_2400</code>	2400 baud
<code>SERIAL_BAUD_4800</code>	4800 baud
<code>SERIAL_BAUD_9600</code>	9600 baud

Use `SetSerialChannel` to specify the transmission channel with the constants described in the following table.

Option	Effect
<code>SERIAL_CHANNEL_IR</code>	IR channel
<code>SERIAL_CHANNEL_PC</code>	PC channel (visible light)

Use `SetSerialPreamblePos` to specify the position of the preamble in the 16 bytes of serial data. Use `SetSerialPreambleLen` to specify the length of the preamble. Use `SetSerialChecksum` to specify the checksum type with the constants described in the following table.

Option	Effect
<code>SERIAL_CHECKSUM_NONE</code>	No checksum
<code>SERIAL_CHECKSUM_SUM</code>	Sum checksum
<code>SERIAL_CHECKSUM_ZERO_SUM</code>	Zero sum checksum

Use `SetSerialBiPhase` to specify the bi-phase mode with the constants described in the following table.

Option	Effect
<code>SERIAL_BIPHASE_OFF</code>	No bi-phase
<code>SERIAL_BIPHASE_ON</code>	Use bi-phase

SetSerialComm(settings)

Function - RCX2

Set the communication settings, which determine how the bits are sent over IR

```
SetSerialComm(SERIAL_COMM_DEFAULT);
```

SetSerialPacket(settings)

Function - RCX2

Set the packet settings, which control how bytes are assembled into packets.

```
SetSerialPacket(SERIAL_PACKET_DEFAULT);
```

SetSerialData(n, value)

Function - RCX2, Spy

Set one byte of data in the transmit buffer. N is the index of the byte to set (0-15), and value can be any expression.

```
SetSerialData(3, x); // set byte 3 to x
```

SerialData(n)

Value - RCX2, Spy

Returns the value of a byte in the transmit buffer (NOT received data). N must be a constant between 0 and 15.

```
x = SerialData(7); // read byte #7
```

SendSerial(start, count)

Function - RCX2, Spy

Use the contents of the transmit buffer to build a packet and send it out the IR port (according to the current packet and communication settings). Start and count are both constants that specify the first byte and the number of bytes within the buffer to be sent.

```
SendSerial(0,2); // send first two bytes in buffer
```

InitSpybotComm()

Function - RCX2

Use this function to configure the serial communication registers in preparation for sending messages using the Spybot protocol.

```
InitSpybotComm(); // prepare IR using Spybot protocol
```

SendSpybotMsg()

Function - RCX2

Use this function to send a 7 byte Spybot message which was previously set via a call to SetSpybotMessage.

```
SendSpybotMsg();
```

SetSpybotMessage(mode, myID, addr, cmd, hi, lo) Function - RCX2

Use this function to set the contents of a Spybot message. The message can then be sent repeatedly via calls to SendSpybotMsg.

```
SetSpybotMessage(MSG_BROADCAST, 9, 0, CMD_FIRE_LASER, 1,
100);
```

SendSpybotMessage(mode, myID, addr, cmd, hi, lo) Function - RCX2

Use this function to send a 7 byte Spybot message. This function calls InitSpybotComm, SetSpybotMessage, and SendSpybotMsg in sequence.

```
SendSpybotMessage(MSG_BROADCAST, 9, 0, CMD_FIRE_LASER, 1,
100);
```

SendSpybotCtrlMsg() Function - RCX2

Use this function to send a 2 byte Spybot controller message which was previously set via a call to SetSpybotCtrlMessage.

```
SendSpybotCtrlMsg();
```

SetSpybotCtrlMessage(nMyID, nMsg) Function - RCX2

Use this function to set the contents of a Spybot controller message. The message can then be sent repeatedly via calls to SendSpybotCtrlMsg.

```
SetSpybotCtrlMessage(ID_CTRL_1, SPY_CTRL_BTN_1);
```

SendSpybotCtrlMessage(nMyID, nMsg) Function - RCX2

Use this function to send a 2 byte Spybot controller message. This function calls InitSpybotComm, SetSpybotCtrlMessage, and SendSpybotCtrlMsg in sequence.

```
SendSpybotCtrlMessage(ID_CTRL_1, SPY_CTRL_BTN_1);
```

SendSpybotCtrlPingMsg() Function - RCX2

Use this function to send a 2 byte Spybot controller ping message which was previously set via a call to SetSpybotCtrlPingMessage.

```
SendSpybotCtrlPingMsg();
```

SetSpybotCtrlPingMessage(nID)

Function - RCX2

Use this function to set the contents of a Spybot controller ping message. The message can then be sent repeatedly via calls to `SendSpybotCtrlPingMsg`.

```
SetSpybotCtrlPingMessage( ID_CTRL_1 );
```

SendSpybotCtrlPingMessage(nID)

Function - RCX2

Use this function to send a 2 byte Spybot controller ping message. This function calls `InitSpybotComm`, `SetSpybotCtrlPingMessage`, and `SendSpybotCtrlPingMsg` in sequence.

```
SendSpybotCtrlPingMessage( ID_CTRL_1 );
```

SendSpybotPingMsg()

Function - RCX2

Use this function to send a 4 byte Spybot ping message which was previously set via a call to `SetSpybotPingMessage`.

```
SendSpybotPingMsg();
```

SetSpybotPing(nLinkID, nMyID, nInfo)

Function – RCX2

Use this function to set the contents of a Spybot ping message. The message can then be sent repeatedly via calls to `SendSpybotPingMsg`.

```
SetSpybotPingMessage( ID_CTRL_1, ID_MIN_BOT+1, 10 );
```

SendSpybotPing(nLinkID, nMyID, nInfo)

Function - RCX2

Use this function to send a 2 byte Spybot ping message. This function calls `InitSpybotComm`, `SetSpybotPingMessage`, and `SendSpybotPingMsg` in sequence.

```
SendSpybotPingMessage( ID_CTRL_1, ID_MIN_BOT+1, 10 );
```

InitRCComm()

Function - RCX2

Use this function to configure the serial communication registers in preparation for sending messages using the Spybot RC protocol.

```
InitRCComm(); // prepare to send IR using RC protocol
```

SendRCMsg()

Function - RCX2

Use this function to send a 4 byte RC message which was previously set via a call to `SetRCMessage`.

```
SendRCMsg();
```

SetRCMessage(nChannel, nLeft, nRight)

Function - RCX2

Use this function to set the contents of a Spybot RC message. The message can then be sent repeatedly via calls to `SendRCMsg`.

```
SetRCMessage(RC_CHANNEL_2, RC_CMD_FWD, RC_CMD_FWD);
```

SendRCMessage(nChannel, nLeft, nRight)

Function - RCX2

Use this function to send a 2 byte Spybot ping message. This function calls `InitRCComm`, `SetRCMessage`, and `SendRCMsg` in sequence.

```
SendRCMessage(RC_CHANNEL_2, RC_CMD_FWD, RC_CMD_FWD);
```

DefaultSerialComm()

Value - Swan

Returns the default UART transmit parameter configuration.

```
x = DefaultSerialComm(); // read default UART xmit config
```

DefaultSerialPacket()

Value - Swan

Returns the default packet data formatting configuration.

```
x = DefaultSerialPacket(); // read default packet config
```

SetDefaultSerialComm(settings)

Function - Swan

Set the default communication settings, which determine how the bits are sent over IR

```
SetDefaultSerialComm(SERIAL_COMM_DEFAULT);
```

SetDefaultSerialPacket(settings)

Function - Swan

Set the default packet settings, which control how bytes are assembled into packets.

```
SetDefaultSerialPacket(SERIAL_PACKET_DEFAULT);
```

SerialType()

Value - Spy

Returns the type of the serial transmission.

```
x = SerialType(); // SERIAL_TYPE_USER ??
```

SetSerialType(type)

Function - Spy

Sets the type of the serial transmission.

```
SetSerialType(SERIAL_TYPE_USER); // set type to user
```

Use one of the following constants: SERIAL_TYPE_SPYBOT, SERIAL_TYPE_RCX, SERIAL_TYPE_RC, SERIAL_TYPE_USER.

SerialBaud()

Value - Spy

Returns the baud rate of the serial transmission.

```
x = SerialBaud(); // SERIAL_BAUD_2400 ??
```

SetSerialBaud(baud)

Function - Spy

Sets the baud rate of the serial transmission.

```
SetSerialBaud(SERIAL_BAUD_2400); // set baud to 2400
```

Use one of the following constants: SERIAL_BAUD_2400, SERIAL_BAUD_4800, SERIAL_BAUD_9600.

SerialChannel()

Value - Spy

Returns the transmission channel.

```
x = SerialChannel(); // SERIAL_CHANNEL_PC ??
```

SetSerialChannel(channel)

Function - Spy

Sets the transmission channel.

```
SetSerialChannel(SERIAL_CHANNEL_IR); // set channel to IR
```

Use one of the following constants: SERIAL_CHANNEL_IR, SERIAL_CHANNEL_PC.

SerialPreamblePos() **Value - Spy**

Returns the preamble position within the serial data buffer.

```
x = SerialPreamblePos();
```

SetSerialPreamblePos(n) **Function - Spy**

Sets the position of the preamble within the serial data buffer.

```
SetSerialPreamblePos(12); // set preamble pos to 12
```

SerialPreambleLen() **Value - Spy**

Returns the preamble length.

```
x = SerialPreambleLen();
```

SetSerialPreambleLen(n) **Function - Spy**

Sets the length of the preamble.

```
SetSerialPreambleLen(3); // set preamble length to 3
```

SerialChecksum() **Value - Spy**

Returns the transmission checksum type.

```
x = SerialChecksum(); // SERIAL_CHECKSUM_SUM ??
```

SetSerialChecksum(check) **Function - Spy**

Sets the transmission checksum type.

```
SetSerialChecksum(SERIAL_CHECKSUM_SUM); // use Sum checksum
```

Use one of the following constants: SERIAL_CHECKSUM_NONE,
SERIAL_CHECKSUM_SUM, SERIAL_CHECKSUM_ZERO_SUM.

SerialBiPhase() **Value - Spy**

Returns the transmission bi-phase mode.

```
x = SerialBiPhase(); // SERIAL_BIPHASE_OFF ??
```

SetSerialBiPhase(mode)

Function - Spy

Sets the transmission bi-phase mode.

```
SetSerialBiPhase(SERIAL_BIPHASE_OFF); // no bi-phase
```

Use one of the following constants: SERIAL_BIPHASE_OFF,
SERIAL_BIPHASE_ON.

3.5.3VLL

Scout, Spy

SendVLL(value)

Function – Scout, Spy

Sends a Visible Light Link (VLL) command, which can be used to communicate with the MicroScout or Code Pilot. The specific VLL commands are described in the Scout SDK.

```
SendVLL(4); // send VLL command #4
```

3.6 Timers

All targets provide several independent timers with 100ms resolution (10 ticks per second). The Scout provides 3 such timers while the RCX, Swan, CyberMaster and Spybotics provide 4. The timers wrap around to 0 after 32767 ticks (about 55 minutes). The value of a timer can be read using `Timer(n)`, where `n` is a constant that determines which timer to use (0-2 for Scout, 0-3 for the others). RCX2, Swan, and Spybotics provide the ability to read the same timers with higher resolution by using `FastTimer(n)`, which returns the timer's value with 10ms resolution (100 ticks per second).

ClearTimer(n)

Function - All

Reset the specified timer to 0.

```
ClearTimer(0);
```

Timer(n)

Value - All

Return the current value of specified timer (in 100ms resolution).

```
x = Timer(0);
```

SetTimer(n, value)

Function - RCX2, Spy

Set a timer to a specific value (which may be any expression).

```
SetTimer(0, x);
```

FastTimer(n)

Value - RCX2, Spy

Return the current value of specified timer in 10ms resolution.

```
x = FastTimer(0);
```

3.7 Counters

RCX2, Scout, Spy

Counters are like very simple variables that can be incremented, decremented, and cleared. The Scout provides two counters (0 and 1), while RCX2, Swan, and Spybotics provide three (0, 1, and 2). In the case of RCX2, Swan, and Spybotics, these counters are overlapped with global storage locations 0-2, so if they are going to be used as counters, a `#pragma reserve` should be used to prevent NQC from using the storage location for a regular variable. For example, to use counter 1:

```
#pragma reserve 1
```

ClearCounter(n)

Function - RCX2, Scout, Spy

Reset counter n to 0. N must be 0 or 1 for Scout, 0-2 for RCX2 and Spybotics.

```
ClearCounter(1);
```

IncCounter(n)

Function - RCX2, Scout, Spy

Increment counter n by 1. N must be 0 or 1 for Scout, 0-2 for RCX2 and Spybotics.

```
IncCounter(1);
```

DecCounter(n)

Function - RCX2, Scout, Spy

Decrement counter n by 1. N must be 0 or 1 for Scout, 0-2 for RCX2 and Spybotics.

```
DecCounter(1);
```

Counter(n)

Value - RCX, Scout, Spy

Return the current value of counter n. N must be 0 or 1 for Scout, 0-3 for RCX2 and Spybotics.

```
x = Counter(1);
```

3.8 Access Control

RCX2, Scout, Spy

Access control is implemented primarily by the `acquire` statement. The `SetPriority` function can be used to set a task's priority, and the following constants may be used to specify resources in an `acquire` statement. Note that the user defined resources are only available on the RCX2 and Swan.

Constant	Resource
ACQUIRE_OUT_A, ACQUIRE_OUT_B, ACQUIRE_OUT_C	outputs
ACQUIRE_SOUND	sound
ACQUIRE_LED	LEDs (Spybotics only)
ACQUIRE_USER_1, ACQUIRE_USER_2, ACQUIRE_USER_3, ACQUIRE_USER_4	user defined - RCX2 and Swan only

SetPriority(p)

Function - RCX2, Scout, Spy

Set a task's priority to p, which must be a constant. RCX2, Swan, and Spybotics support priorities 0-255, while Scout supports priorities 0-7. Note that lower numbers are higher priority.

```
SetPriority(1);
```

3.9 Events

RCX2, Scout

Although the RCX2, Swan, Scout, and Spybotics share a common event mechanism, the RCX2, Swan, and Spybotics provide 16 completely configurable events while the Scout

has 15 predefined events. The only functions common to both targets are the commands to inspect or force events.

ActiveEvents(task)

Value - RCX2, Scout, Spy

Return the set of events that have been triggered for a given task.

```
x = ActiveEvents(0);
```

CurrentEvents()

Value - RCX2, Spy

Return the set of events that have been triggered for the active task.

```
x = CurrentEvents();
```

Event(events)

Function - RCX2, Scout, Spy

Manually triggers the specified events. This can be useful in testing event handling of the program, or in other cases simulating an event based on other criteria. Note that the specification of the events themselves is slightly different between brick types. RCX2, Swan, and Spybotics use the `EVENT_MASK` macro to compute an event mask, while Scout has predefined masks.

```
Event(EVENT_MASK(3)); // triggering an RCX2 event  
Event(EVENT_1_PRESSED); // triggering a Scout event
```

3.9.1 Configurable Events

RCX2, Spy

RCX2, Swan, and Spybotics provide an extremely flexible event system. There are 16 events, each of which can be mapped to one of several event sources (the stimulus that can trigger the event), and an event type (the criteria for triggering). A number of other parameters may also be specified depending on the event type. For all of the configuration calls an event is identified by its event number - a constant from 0 to 15.

Legal event sources are sensors, timers, counters, or the message buffer. An event is configured by calling `SetEvent(event, source, type)`, where `event` is a constant event number (0-15), `source` is the event source itself, and `type` is one of the types shown below (some combinations of sources and types are illegal).

NQC Programmer's Guide

Event Type	Condition	Event Source
EVENT_TYPE_PRESSED	value becomes <i>on</i>	sensors only
EVENT_TYPE_RELEASED	value becomes <i>off</i>	sensors only
EVENT_TYPE_PULSE	value goes from <i>off</i> to <i>on</i> to <i>off</i>	sensors only (RCX2)
EVENT_TYPE_EDGE	value goes from <i>on</i> to <i>off</i> or vice versa	sensors only (RCX2)
EVENT_TYPE_FASTCHANGE	value changes rapidly	sensors only (RCX2)
EVENT_TYPE_LOW	value becomes <i>low</i>	any
EVENT_TYPE_NORMAL	value becomes <i>normal</i>	any
EVENT_TYPE_HIGH	value becomes <i>high</i>	any
EVENT_TYPE_CLICK	value from <i>low</i> to <i>high</i> back to <i>low</i>	any
EVENT_TYPE_DOUBLECLICK	two clicks within a certain time	Any (RCX2)
EVENT_TYPE_MESSAGE	new message received	Message() only (RCX2)
EVENT_TYPE_ENTRY_FOUND	World entry found	VLL() only (Spy)
EVENT_TYPE_MSG_DISCARD	Message discarded	VLL() only (Spy)
EVENT_TYPE_MSG_RECEIVED	Message received	VLL() only (Spy)
EVENT_TYPE_VLL_MSG_RECEIVED	Message received	VLL() only (Spy)
EVENT_TYPE_ENTRY_CHANGED	World entry changed	VLL() only (Spy)

EVENT_TYPE_4

The first four event types make use of a sensor's boolean value, thus are most useful with touch sensors. For example, to set event #2 to be triggered when a touch sensor on port 1 is pressed, the following call could be made:

```
SetEvent(2, SENSOR_1, EVENT_TYPE_PRESSED);
```

In order for `EVENT_TYPE_PULSE` or `EVENT_TYPE_EDGE` to be used, the sensor must be configured in the `SENSOR_MODE_PULSE` or `SENSOR_MODE_EDGE` respectively.

`EVENT_TYPE_FASTCHANGE` should be used with sensors that have been configured with a slope parameter. When the raw value changes faster than the slope parameter an `EVENT_TYPE_FASTCHANGE` event will be triggered.

The next three types (`EVENT_TYPE_LOW`, `EVENT_TYPE_NORMAL`, and `EVENT_TYPE_HIGH`) convert an event source's value into one of three ranges (low, normal, or high), and trigger an event when the value moves from one range into another. The ranges are defined by the *lower limit* and *upper limit* for the event. When the source value is lower than the lower limit, the source is considered low. When the source value is higher than the upper limit, the source is considered high. The source is normal whenever it is between the limits.

The following example configures event #3 to trigger when the sensor on port 2's value goes into the high range. The upper limit is set for 80, and the lower limit is set for 50. This configuration is typical of how an event can be triggered when a light sensor detected a bright light.

```
SetEvent(3, SENSOR_2, EVENT_TYPE_HIGH);  
SetLowerLimit(3, 50);  
SetUpperLimit(3, 80);
```

A hysteresis parameter can be used to provide more stable transitions in cases where the source value may jitter. Hysteresis works by making the transition from low to normal a little higher than the transition from normal to low. In a sense, it makes it easier to get into the low range than get out of it. A symmetrical case applies to the transition between normal and high.

A transition from low to high back to low will trigger a `EVENT_TYPE_CLICK` event, provided that the entire sequence is faster than the *click time* for the event. If two

successive clicks occur and the time between clicks is also less than the click time, then an `EVENT_TYPE_DOUBLECLICK` event will be triggered. The system also keeps track of the total number of clicks for each event.

The last event type, `EVENT_TYPE_MESSAGE`, is only valid when `Message()` is used as the event source. The event will be triggered whenever a new message arrives (even if its value is the same as a previous message).

The monitor statement and some API functions (such as `ActiveEvents()` or `Event()`) need to handle multiple events. This is done by converting each event number to an event mask, and then combining the masks with a bitwise OR. The `EVENT_MASK(event)` macro converts an event number to a mask. For example, to monitor events 2 and 3, the following statement could be used:

```
monitor(EVENT_MASK(2) | EVENT_MASK(3))
```

SetEvent(event, source, type)

Function - RCX2, Spy

Configure an event (a number from 0 to 15) to use the specified source and type. Both event and type must be constants, and source should be the actual source expression.

```
SetEvent(2, Timer(0), EVENT_TYPE_HIGH);
```

ClearEvent(event)

Value - RCX2, Spy

Clear the configuration for the specified event. This prevents it from triggering until it is re-configured.

```
ClearEvent(2); // clear event #2
```

ClearAllEvents()

Value - RCX2, Spy

Clear the configurations for all events.

```
ClearAllEvents();
```

EventState(event)

Value - RCX2, Spy

Return the state of a given event. States are 0: Low, 1: Normal, 2: High, 3: Undefined, 4: Start calibrating, 5: Calibrating in process.

```
x = EventState(2);
```

CalibrateEvent(event, lower, upper, hyst) Function - RCX2, Spy

Calibrate the event by taking an actual sensor reading and then applying the specified lower, upper, and hyst ratios to determine actual limits and hysteresis value. The specific formulas for calibration depend on sensor type and are explained in the LEGO SDK. Calibration is not instantaneous - EventState() can be checked to determine when the calibration is complete (typically about 50ms).

```
CalibrateEvent(2, 50, 50, 20);  
until(EventState(2) != 5); // wait for calibration
```

SetUpperLimit(event, limit) Function - RCX2, Spy

Set the upper limit for the event, where event is a constant event number and limit can be any expression.

```
SetUpperLimit(2, x); // set upper limit for #2 to x
```

UpperLimit(event) Value - RCX2, Spy

Return the current upper limit for the specified event number.

```
x = UpperLimit(2); // get upper limit for event 2
```

SetLowerLimit(event, limit) Function - RCX2, Spy

Set the lower limit for the event, where event is a constant event number and limit can be any expression.

```
SetLowerLimit(2, x); // set lower limit for #2 to x
```

LowerLimit(event) Value - RCX2, Spy

Return the current lower limit for the specified event number.

```
x = LowerLimit(2); // get lower limit for event 2
```

SetHysteresis(event, value) Function - RCX2, Spy

Set the hysteresis for the event, where event is a constant event number and value can be any expression.

```
SetHysteresis(2, x);
```

Hysteresis(event)

Value - RCX2, Spy

Return the current hysteresis for the specified event number.

```
x = Hysteresis(2);
```

SetClickTime(event, value)

Function - RCX2, Spy

Set the click time for the event, where event is a constant event number and value can be any expression. The time is specified in increments of 10ms, so one second would be a value of 100.

```
SetClickTime(2, x);
```

ClickTime(event)

Value - RCX2, Spy

Return the current click time for the specified event number.

```
x = ClickTime(2);
```

SetClickCounter(event, value)

Function - RCX2

Set the click counter for the event, where event is a constant event number and value can be any expression.

```
SetClickCounter(2, x);
```

ClickCounter(event)

Value - RCX2

Return the current click counter for the specified event number.

```
x = ClickCounter(2);
```

3.9.2 Scout Events

Scout

The Scout provides 15 events, each of which has a predefined meaning as shown in the table below.

Event Name	Condition
EVENT_1_PRESSED	sensor 1 pressed

EVENT_1_RELEASED	sensor 1 released
EVENT_2_PRESSED	sensor 2 pressed
EVENT_2_RELEASED	sensor 2 released
EVENT_LIGHT_HIGH	light sensor "high"
EVENT_LIGHT_NORMAL	light sensor "normal"
EVENT_LIGHT_LOW	light sensor "low"
EVENT_LIGHT_CLICK	low to high to low
EVENT_LIGHT_DOUBLECLICK	two clicks
EVENT_COUNTER_0	counter 0 over limit
EVENT_COUNTER_1	counter 1 over limit
EVENT_TIMER_0	timer 0 over limit
EVENT_TIMER_1	timer 1 over limit
EVENT_TIMER_2	timer 2 over limit
EVENT_MESSAGE	new message received

The first four events are triggered by touch sensors connected to the two sensor ports.

EVENT_LIGHT_HIGH, EVENT_LIGHT_NORMAL, and EVENT_LIGHT_LOW are triggered by the light sensor's value changing from one range to another. The ranges are defined by `SetSensorUpperLimit`, `SetSensorLowerLimit`, and `SetSensorHysteresis` which were described previously.

EVENT_LIGHT_CLICK and EVENT_LIGHT_DOUBLECLICK are also triggered by the light sensor. A click is a transition from low to high and back to low within a certain amount of time, called the *click time*.

Each counter has a counter limit. When the counter exceeds this limit, EVENT_COUNTER_0 or EVENT_COUNTER_1 is triggered. Timers also have a limit, and they generate EVENT_TIMER_0, EVENT_TIMER_1, and EVENT_TIMER_2.

EVENT_MESSAGE is triggered whenever a new IR message is received.

SetSensorClickTime(value)

Function - Scout

Set the click time used to generate events from the light sensor. Value should be specified in increments of 10ms, and may be any expression.

```
SetSensorClickTime(x);
```

SetCounterLimit(n, value)

Function - Scout

Set the limit for counter n. N must be 0 or 1, and value may be any expression.

```
SetCounterLimit(0, 100); // set counter 0 limit to 100
```

SetTimerLimit(n, value)

Function - Scout

Set the limit for timer n. N must be 0, 1, or 2, and value may be any expression.

```
SetTimerLimit(1, 100); // set timer 1 limit to 100
```

3.10 Data Logging

RCX

The RCX contains a datalog which can be used to store readings from sensors, timers, variables, and the system watch. Before adding data, the datalog first needs to be created using the `CreateDatalog(size)` command. The 'size' parameter must be a constant and determines how many data points the datalog can hold.

```
CreateDatalog(100); // datalog for 100 points
```

Values can then be added to the datalog using `AddToDatalog(value)`. When the datalog is uploaded to a computer it will show both the value itself and the source of the value (timer, variable, etc). The datalog directly supports the following data sources: timers, sensor values, variables, and the system watch. Other data types (such as a constant or random number) may also be logged, but in this case NQC will first move the value into a variable and then log the variable. The values will still be captured faithfully in the datalog, but the sources of the data may be a bit misleading.

```
AddToDatalog(Timer(0)); // add timer 0 to datalog
AddToDatalog(x); // add variable 'x'
AddToDatalog(7); // add 7 - will look like a variable
```

The RCX itself cannot read values back out of the datalog. The datalog must be uploaded to a host computer. The specifics of uploading the datalog depend on the NQC

environment being used. For example, in the command line version of NQC, the following commands will upload and print the datalog:

```
nqc -datalog
nqc -datalog_full
```

The Swan (and the standard LEGO firmware version 3.30 which is available via the ROBOLAB software) adds the ability to read values and types out of the datalog. New firmware sources are used to implement this functionality. Use the `DatalogType`, `DatalogValue`, and `DatalogByte` functions to programmatically access these sources.

CreateDatalog(size)

Function - RCX

Create a datalog of the specified *size* (which must be a constant). A size of 0 clears the existing datalog without creating a new one.

```
CreateDatalog(100); // datalog for 100 points
```

AddToDatalog(value)

Function - RCX

Add the *value*, which may be an expression, to the datalog. If the datalog is full the call has no effect.

```
AddToDatalog(x);
```

UploadDatalog(start, count)

Function - RCX

Initiate and upload of *count* data points beginning at *start*. This is of relatively little use since the host computer usually initiates the upload.

```
UploadDatalog(0, 100); // upload entire 100 point log
```

DatalogType(n)

Value – Swan (and RCX2+)

Read or write the 8-bit datalog type specified by the parameter. If a variable is used the type is read or written indirectly.

```
x = DatalogType(0);
```

DatalogValue(n)

Value – Swan (and RCX2+)

Read or write the 16-bit datalog value specified by the parameter. If a variable is used the value is read or written indirectly.

```
x = DatalogValue(0);
```

DatalogByte(n)

Value – Swan (and RCX2+)

Read or write the 8-bit datalog byte specified by the parameter. If a variable is used the byte is read or written indirectly.

```
x = DatalogByte(0);
```

3.11 General Features

Wait(time)

Function - All

Make a task sleep for specified amount of time (in 100ths of a second). The time argument may be an expression or a constant:

```
Wait(100); // wait 1 second  
Wait(Random(100)); // wait random time up to 1 second
```

StopAllTasks()

Function - All

Stop all currently running tasks. This will halt the program completely, so any code following this command will be ignored.

```
StopAllTasks(); // stop the program
```

Random(n)

Value - All

Return a random number between 0 and n. N must be a constant.

```
x = Random(10);
```

SetRandomSeed(n)

Function - RCX2, Spy

Seed the random number generator with n. N may be an expression.

```
SetRandomSeed(x); // seed with value of x
```

BatteryLevel()

Value - RCX2, Spy

Return the battery level in millivolts.

```
x = BatteryLevel();
```

FirmwareVersion()

Value - RCX2, Spy

Return the firmware version as an integer. For example, version 3.2.6 is 326.

```
x = FirmwareVersion();
```

SetSleepTime(minutes)

Function - All

Set the sleep timeout the requested number of minutes (which must be a constant).

Specifying 0 minutes disables the sleep feature.

```
SetSleepTime(5); // sleep after 5 minutes  
SetSleepTime(0); // disable sleep time
```

SleepNow()

Function - All

Force the device to go to sleep. Only works if the sleep time is non-zero.

```
SleepNow(); // go to sleep
```

Indirect(n)

Value - RCX2, Spy

Read the value of a variable indirectly. The parameter is the address of a global variable whose value is the address of the variable you wish to read.

```
x = Indirect(0); // the value of var pointed to by var 0
```

SetIndirectVar(const int &v, const int &n)

Value - RCX2, Spy

Set the value of a variable indirectly. The first parameter is the global variable whose value is the address of the variable you wish to set. The second parameter is the value you wish to set it to.

```
SetIndirectVar(x, 200);
```

3.12 RCX Specific Features

Program()

Value - RCX

Number of the currently selected program.

```
x = Program();
```

SelectProgram(n)

Function - RCX2

Select the specified program and start running it. Note that programs are numbered 0-4 (not 1-5 as displayed on the LCD).

```
SelectProgram(3);
```

Watch()

Value - RCX

Return the value of the system clock in minutes.

```
x = Watch();
```

SetWatch(hours, minutes)

Function - RCX

Set the system watch to the specified number of hours and minutes. Hours must be a constant between 0 and 23 inclusive. Minutes must be a constant between 0 and 59 inclusive.

```
SetWatch(3, 15); // set watch to 3:15
```

3.13 Scout Specific Features

SetScoutRules(motion, touch, light, time, fx)

Function - Scout

Set the various rules used by the scout in stand-alone mode.

ScoutRules(n)

Value - Scout

Return current setting for one of the rules. N should be a constant between 0 and 4.

```
x = ScoutRules(1); // get setting for rule #1
```

SetScoutMode(mode)

Function - Scout

Put the scout into stand-alone (0) or power (1) mode. As a programming call it really only makes sense to put into stand-alone mode since it would already be in power mode to run an NQC program.

SetEventFeedback(events)

Function - Scout

Set which events should be accompanied by audio feedback.

```
SetEventFeedback( EVENT_1_PRESSED );
```

EventFeedback()

Value - Scout

Return the set of events that have audio feedback.

```
x = EventFeedback();
```

SetLight(mode)

Function - Scout

Control the Scout's LED. Mode must be LIGHT_ON or LIGHT_OFF.

```
SetLight(LIGHT_ON); // turn on LED
```

3.14 CyberMaster Specific Features

CyberMaster provides alternate names for the sensors: SENSOR_L, SENSOR_M, and SENSOR_R. It also provides alternate names for the outputs: OUT_L, OUT_R, OUT_X. Additionally, the two internal motors have tachometers, which measure 'clicks' and speed as the motors turn. There are about 50 clicks per revolution of the shaft. The tachometers can be used, for example, to create a robot which can detect if it has bumped into an object without using any external sensors. The tachometers have maximum values of 32767 and do not differentiate between directions. They will also count up if the shaft is turned by hand, including when no program is running.

Drive(motor0, motor1)

Function - CM

Turns on both motors at the power levels specified. If a power level is negative, then the motor will run in reverse. Equivalent to this code:

```
SetPower(OUT_L, abs(power0));
SetPower(OUT_R, abs(power1));
if(power0 < 0)
    { SetDirection(OUT_L, OUT_REV) }
else
    { SetDirection(OUT_L, OUT_FWD) }
if(power1 < 0)
    { SetDirection(OUT_R, OUT_REV) }
else
    { SetDirection(OUT_R, OUT_FWD) }
SetOutput(OUT_L + OUT_R, OUT_ON);
```

OnWait(motors, n time)

Function - CM

Turns on the motors specified, all at the same power level then waits for the given time. The time is in 10ths of a second, with a maximum of 255 (or 25.5 seconds). Equivalent to this code:

```
SetPower(motors, abs(power));
if(power < 0)
    { SetDirection(motors, OUT_REV) }
else
    { SetDirection(motors, OUT_FWD) }
SetOutput(motors, OUT_ON);
Wait( time * 10 );
```

OnWaitDifferent(motors, n0, n1, n2, time)

Function - CM

Like OnWait(), except different power levels can be given for each motor.

ClearTachoCounter(motors)

Function - CM

Resets the tachometer for the motor(s) specified.

TachoCount(n)

Value - CM

Returns the current value of the tachometer for a specified motor.

TachoSpeed(n)

Value - CM

Returns the current speed of the tachometer for a specified motor. The speed is fairly constant for an unladen motor at any speed, with a maximum value of 90. (This will

be lower as your batteries lose power!) The value drops as the load on the motor increases. A value of 0 indicates that the motor is stalled.

ExternalMotorRunning()

Value - CM

This is actually a measure of the current being drawn by the motor. The values returned tends to fluctuate slightly, but are, on average, as follows for an unladen motor:

0 motor is floating

1 motor is off

<=7 motor is running at around this power level. This is where the value fluctuates the most (probably related to the PWM method used to drive the motors.) In any case, you should know what power level you set the motor to in the first place.

The value increases as the load on the motor increases, and a value between 260 and 300 indicates that the motor has stalled.

AGC()

Value - CM

Return the current value of the automatic gain control on the RF receiver. This can be used to give a very rough (and somewhat inaccurate) measure of the distance between the CyberMaster and the RF transmitter.

```
x = AGC();
```

3.15 Spybotics Specific Features

SetLED(mode, value)

Function - Spy

A single command, `SetLED(mode, value)`, can be used to control all of the different LEDs on the Spybotics brick. The function takes two arguments, a mode and a value. The mode parameter selects which group of LEDs to control, and how they should be affected.

LED Mode Constants

```
LED_MODE_ON, LED_MODE_BLINK, LED_MODE_DURATION,  
LED_MODE_SCALE, LED_MODE_SCALE_BLINK,  
LED_MODE_SCALE_DURATION, LED_MODE_RED_SCALE,  
LED_MODE_RED_SCALE_BLINK, LED_MODE_GREEN_SCALE,  
LED_MODE_GREEN_SCALE_BLINK, LED_MODE_YELLOW,  
LED_MODE_YELLOW_BLINK, LED_MODE_YELLOW_DURATION,  
LED_MODE_VLL, LED_MODE_VLL_BLINK, LED_MODE_VLL_DURATION
```

The meaning of value parameter depends on the mode. Sometimes it is a mask of which LEDs should be controlled (as with `LED_MODE_ON`). Sometimes it is a single value that is used to determine how many LEDs to turn on (as with `LED_MODE_SCALE`).

LED Value Constants

```
LED_RED1, LED_RED2, LED_RED3, LED_GREEN1, LED_GREEN2,  
LED_GREEN3, LED_YELLOW, LED_ALL_RED, LED_ALL_GREEN,  
LED_ALL_RED_GREEN, LED_ALL
```

Here is a short program that blinks all six of the top red/green LEDs.

```
task main()  
{  
    SetLED(LED_MODE_BLINK, LED_ALL_RED_GREEN);  
    Wait(200);  
}
```

LED(mode)

Value - Spy

Return the value of the LED control registers. Use the LED Mode constants as the parameter.

```
x = LED(LED_MODE_ON);
```

SetAnimation(number)

Function - Spy

A more sophisticated way to control the top LEDs is to use animations. An animation is a sequence of LED patterns. Each pattern is displayed for a certain amount of time, then the next pattern is displayed. Animations are activated using the `SetAnimation(number)` function. There are 8 pre-defined animations in ROM.

ROM Animation Constants

```
ANIMATION_SCAN, ANIMATION_SPARKLE, ANIMATION_FLASH,  
ANIMATION_RED_TO_GREEN, ANIMATION_GREEN_TO_RED,
```

```
ANIMATION_POINT_FORWARD, ANIMATION_ALARM,  
ANIMATION_THINKING
```

Here is a short program that runs a ROM animation.

```
task main()  
{  
  SetAnimation(ANIMATION_SCAN);  
  Wait(200);  
}
```

ANIMATION

Resource Declaration - Spy

It is also possible to define custom animations. This is done with a resource declaration (a new NQC feature). The declaration must be done at the global level (not within a task/sub/function), and must occur before the animation is used in the program. An animation declaration looks like this:

```
ANIMATION name { data ... };
```

Where *name* is a name you pick for the animation, and *data* is a series of bytes that determine the animation's appearance. The data bytes are interpreted in pairs, with the first byte of each pair specifying a mask of the LEDs that should be turned on, and the second byte determining how many 10ms ticks that pattern should be displayed for. A pair of 255,0 causes the animation to loop continuously. You can also use the following two special commands (in a comma-separated list) to define an animation:

Animation Commands

```
AnimateLED(led_mask, time)  
RepeatAnimation()
```

Once the animation is declared, its name may be used as an argument to `SetAnimation()`. Here is an example:

```
ANIMATION my_animation {  
  AnimateLED(1, 10),  
  AnimateLED(2, 10),  
  AnimateLED(4, 10),  
  AnimateLED(2, 10),  
  RepeatAnimation()  
};  
  
task main()
```

```
{
  SetAnimation(my_animation);
  Wait(500);
}
```

AnimateLED(led_mask, time)

Animation Macro - Spy

User animations contain LED patterns. The `led_mask` parameter is a mask of the LEDs that should be turned on (see the LED value constants defined above). The time parameter is the number of 10 ms steps to display the pattern for, ranging from 1 to 255 (2.55 seconds).

```
AnimationLED(LED_RED1, 10)
```

RepeatAnimation()

Animation Macro - Spy

Repeat the user animation from the beginning.

```
RepeatAnimation()
```

SOUNDEFFECT

Resource Declaration - Spy

With Spybotics you can define up to 15 of your own sound effects using a resource declaration. The declaration must be done at the global level (not within a task/sub/function), and must occur before the sound effect is used in the program. A sound effect declaration looks like this:

```
SOUNDEFFECT name { data ... };
```

Where *name* is a name you pick for the sound effect, and *data* is a series of bytes that determine the sound effect sound. Use the following special commands (in a comma-separated list) to define the sound effect.

User Sound Effect Commands

```
Gate(on, period)
GateOff()
Glide(freq1, freq2, time)
Vibrato(freq1, freq2, time)
WaitEffect(time)
FixedWaitEffect(time)
Tone(freq, time)
FixedTone(freq, time)
RepeatEffect()
```

Once the sound effect is declared, its name may be used as an argument to `PlaySound()`. Here is an example:

```
SOUNDEFFECT my_effect {
  Gate(1, 10),
  Glide(294, 660, 60),
  GateOff(),
  WaitEffect(50),
  Vibrato(294, 660, 60),
  FixedTone(500, 50),
  RepeatEffect()
};

task main()
{
  PlaySound(my_effect);
  Wait(500);
}
```

Gate(on, period)

Sound Effect Macro - Spy

User sound effects can be changed by turning the sound on and off rapidly. The on parameter is that portion of the period during which sound is output. The period parameter is the length of the gate cycle in 10 ms steps from 1 to 255 (2.55 seconds).

```
Gate(1, 10)
```

GateOff()

Sound Effect Macro - Spy

Stop gating the sound effect.

```
GateOff()
```

Glide(frequency1, frequency2, duration)

Sound Effect Macro - Spy

User sound effects can contain sounds which glide from one frequency to another. The two frequency parameters can range from 32 to 20000 Hz. The duration parameter is the time to glide from the first frequency to the second in 10 ms steps from 1 to 255 (2.55 seconds).

```
Glide(294, 660, 60)
```

Vibrato(frequency1, frequency2, duration) Sound Effect Macro - Spy

User sound effects can contain vibratos, where the sound alternates rapidly between two frequencies. The two frequency parameters can range from 32 to 20000 Hz. The duration parameter is the number of 10 ms steps from 1 to 255 (2.55 seconds).

```
Vibrato(294, 660, 60)
```

WaitEffect(duration) Sound Effect Macro - Spy

User sound effects can contain wait periods. The duration parameter is the length of the wait in 10 ms steps from 1 to 255 (2.55 seconds).

```
WaitEffect(60)
```

FixedWaitEffect(duration) Sound Effect Macro - Spy

User sound effects can contain fixed wait periods. The duration parameter is the length of the wait in 10 ms steps from 1 to 255 (2.55 seconds). This wait period will be unaffected by adjustments to the sound effect time.

```
FixedWaitEffect(60)
```

Tone(frequency, duration) Sound Effect Macro - Spy

User sound effects can contain simple tones. The frequency parameter is the tone to be played, ranging from 32 to 20000 Hz. The duration parameter is the length of the wait in 10 ms steps from 1 to 255 (2.55 seconds).

```
Tone(440, 60)
```

FixedTone(frequency, duration) Sound Effect Macro - Spy

User sound effects can contain fixed wait periods. The frequency parameter is the tone to be played, ranging from 32 to 20000 Hz. The duration parameter is the length of the wait in 10 ms steps from 1 to 255 (2.55 seconds). This wait period will be unaffected by adjustments to the sound effect sound or time.

```
FixedTone(440, 60)
```

RepeatEffect()

Sound Effect Macro - Spy

Repeat the user sound effect from the beginning.

```
RepeatEffect()
```

EffectSound()

Value - Spy

Return the value of the sound effect frequency adjustment register.

```
x = EffectSound(); // read the sound effect freq adj
```

EffectTime()

Value - Spy

Return the value of the sound effect time adjustment register.

```
x = EffectTime(); // read the sound effect time adj
```

SetEffectSound(s)

Function - Spy

Set the value of the sound effect frequency adjustment register. The parameter can range from 0 to 255 where 100 = 1.0 * the frequency.

```
SetEffectSound(50); // cut freq in half (50%)
```

SetEffectTime(t)

Function - Spy

Set the value of the sound effect time adjustment register. The parameter can range from 0 to 255 where 100 = 1.0 * the duration.

```
SetEffectTime(50); // cut sound duration in half (50%)
```

ClearWorld()

Function - Spy

Clear the contents of the world relationship table.

```
ClearWorld(); // empty world table
```

FindWorld(v, relationSource, criteria, threshold)

Function - Spy

Sets variable v to the next entry in the world relationship table that matches the criteria specified.

```
task main()
{
    int v = -1;
```

```
ClearWorld();
FindWorld(v, SPY_RANGE, REL_GT, RANGE_NOWHERE);
while (v != -1)
{
    SetWorldNote(v, 40);
    SetTargetID(v);
    FindWorld(v, SPY_RANGE, REL_GT, RANGE_NOWHERE);
}
```

Criteria Constants

REL_GT, REL_LT, REL_EQ, REL_NE

Target(n)

Value - Spy

Return the value from the specified relation source for the current target.

```
x = Target(SPY_RANGE); // get the target range
```

Relation Source Constants

SPY_TARGETID, SPY_NOTE, SPY_LINKID, SPY_RANGE,
SPY_DIRECTION, SPY_ASPECT, SPY_INFO, SPY_SHORTID

SetTargetID(v)

Function - Spy

Set the current target based on the value of v. Setting the target to TARGET_NONE stops tracking.

```
int x = 5;
SetTargetID(x); // set the target ID
```

ID Constants

TARGET_NONE, ID_NONE, ID_CTRL1, ID_CTRL2, ID_CTRL3,
ID_CTRL4, ID_CTRL5, ID_CTRL6, ID_PC, ID_BOT_MIN, ID_BOT_MAX

SetTargetNote(v)

Function - Spy

Set the current target's game note.

```
SetTargetNote(50); // set the target's note to 50
```

GetWorld(relationSource, target, v)

Function - Spy

Set variable v to the value in the relationSource for the specified target.

```
GetWorld(SPY_RANGE, t, v); // set v to target t's range
```

GetWorldAspect(t, v)

Function - Spy

Set variable v to the specified target's aspect.

```
GetWorldAspect(t, v); // set v to target t's aspect
```

Aspect Constants

```
ASPECT_FRONT_LEFT, ASPECT_FRONT, ASPECT_FRONT_RIGHT,  
ASPECT_BACK_RIGHT, ASPECT_BACK, ASPECT_BACK_LEFT
```

GetWorldDirection(t, v)

Function - Spy

Set variable v to the value in the relationSource for the specified target.

```
GetWorldDirection(t, v); // set v to target t's direction
```

Direction Constants

```
DIRECTION_LEFT, DIRECTION_LEFT_OF_CENTER, DIRECTION_CENTER,  
DIRECTION_RIGHT_OF_CENTER, DIRECTION_RIGHT
```

GetWorldLinkID(t, v)

Function - Spy

Set variable v to the specified target's link ID.

```
GetWorldLinkID(t, v); // set v to target t's link ID
```

GetWorldNote(t, v)

Function - Spy

Set variable v to the specified target's note.

```
GetWorldNote(t, v); // set v to target t's note
```

GetWorldRange(t, v)

Function - Spy

Set variable v to the specified target's range.

```
GetWorldRange(t, v); // set v to target t's range
```

Range Constants

```
RANGE_NOWHERE, RANGE_ANYWHERE, RANGE_THERE, RANGE_HERE
```

GetWorldShortID(t, v)

Function - Spy

Set variable v to the specified target's short ID.

```
GetWorldShortID(t, v); // set v to target t's short ID
```

SetWorldNote(t, v)

Function - Spy

Set the specified target's note to the value v.

```
SetWorldNote(t, v); // set target t's note
```

Pop(n)

Function - Spy

Pop n entries off the stack.

```
Pop(2); // pop 2 entries off the stack
```

Push(v)

Function - Spy

Push a value onto the stack

```
Push(v); // push the contents of variable v onto the stack
```

Stack(index)

Value - Spy

Return the value at the specified stack index.

```
x = Stack(0); // set x to first stack entry
```

SetStack(index, v)

Function - Spy

Set the stack entry specified by index to the value v.

```
SetStack(0, 4); // set the first stack entry to 4
```

TimerState(n)

Value - Spy

Return the current running state of timer n.

```
x = TimerState(0); // set x to timer 0's state
```

SetTimerState(n, s)

Function - Spy

Set the running state of the specified timer.

```
SetTimerState(0, TIMER_STOPPED); // stop timer 0
```

State Constants

```
TIMER_RUNNING, TIMER_STOPPED
```

EEPROM(n)

Value - Spy

Return the value stored at the EEPROM location specified by index (either directly or indirectly).

```
x = EEPROM(10); // read contents of EEPROM location 10
```

SetEEPROM(i, d)

Function - Spy

Set the EEPROM location specified by index (directly or indirectly) to the value d.

```
SetEEPROM(0, 5); // set EEPROM location 0 to 5
int i = 3;
SetEEPROM(i, TimerState(0)); // set EEPROM location 3
```

CurrentTaskID()

Value - Spy

Return the current task ID.

```
x = CurrentTaskID(); // read current task ID
```

RxMessageLock()

Value - Spy

Return the receive buffer locking value.

```
x = RxMessageLock(); // read the message locking value
```

SetRxMessageLock(lock)

Function - Spy

Set the receive buffer locking value. To lock both IR and PC buffers use MSG_IR+MSG_PC.

```
SetRxMessageLock(MSG_IR); // lock the IR message buffer
```

Receive Message Locking Constants

```
MSG_NONE, MSG_IR, MSG_PC
```

RxMessageIndex()

Value - Spy

Return the index for the latest NewEntry event.

```
x = RxMessageIndex();
```

RxMessageChannel()

Value - Spy

Return the channel containing the latest received message.

```
x = RxMessageChannel();
```

RxMessageID(channel)

Value - Spy

Extract an ID from a received IR or PC message and convert it into an index. The desired channel is MSG_IR or MSG_PC.

```
x = RxMessageID(MSG_IR);
```

RxMessage(channel, byte)

Value - Spy

Read the contents of a received IR or PC message (4 bytes total). The desired channel is MSG_IR or MSG_PC. The desired byte is specified using MSG_INDEX, MSG_COMMAND, MSG_HI_BYTE, or MSG_LO_BYTE.

```
if (RxMessage(MSG_IR, MSG_COMMAND) == COMMAND_CONTROLLER)
{
    x = RxMessage(MSG_IR, MSG_HI_BYTE);
}
```

PingControl(n)

Value - Spy

Return the value of the ping control registers (n = 0..2).

```
x = PingControl(1); // read the current ping interval
```

PingData()

Value - Spy

Return the current 8 bit information for ping messages

```
x = PingData();
```

SetPingData(d)

Function - Spy

Set the 8 bit information for ping messages.

```
SetPingData(55); // send the value 55 when pinging
```

PingInterval()

Value - Spy

Return the current ping interval.

```
x = PingInterval();
```

SetPingInterval(interval)

Function - Spy

Set the ping interval in 10ms steps. Setting the interval to zero will disable pinging.

```
SetPingInterval(0); // disable pings
```

PingID()

Value - Spy

Return the Spybotics ping ID number.

```
x = PingID(); // x = my ping ID
```

BeaconControl(n)

Value - Spy

Return the value of the beacon control registers (n = 0..3).

```
x = BeaconControl(1); // read the RC receive channel
```

LinkID()

Value - Spy

Return the link ID (0-7; 0 = no link, 1-6 control unit ID, 7 = PC).

```
x = LinkID(); // read link ID
```

ID Constants

ID_NONE, ID_CTRL1, ID_CTRL2, ID_CTRL3, ID_CTRL4, ID_CTRL5,
ID_CTRL6, ID_PC

RCRxChannel()

Value - Spy

Return the RC receive channel.

```
x = RCRxChannel(); // read RC receive channel
```

SetRCRxChannel(channel)

Function - Spy

Set the RC receive channel.

```
SetRCRxChannel(RC_CHANNEL_1);
```

RC Channel Constants

RC_CHANNEL_BROADCAST, RC_CHANNEL_1, RC_CHANNEL_2,
RC_CHANNEL_3, RC_CHANNEL_DISABLED

RCTxChannel()

Value - Spy

Return the RC transmit channel.

```
x = RCTxChannel(); // read RC transmit channel
```

SetRCTxChannel(channel)

Function - Spy

Set the RC transmit channel.

```
SetRCTxChannel(RC_CHANNEL_1);
```

RCTxMode()

Value - Spy

Return the current RC transmit mode.

```
x = RCTxMode(); // read RC transmit mode
```

SetRCTxMode(mode)

Function - Spy

Set the RC transmit mode.

```
SetRCTxMode(RCTXMODE_SINGLE_SHOT);
```

RC Tx Mode Constants

```
RCTXMODE_SINGLE_SHOT, RCTXMODE_CONTINUOUS
```

StartTask(task)

Function - Spy

Start a task by numeric value rather than by name.

```
StartTask(9); // start task number 9
```

StopTask(task)

Function - Spy

Stop a task by numeric value rather than by name.

```
StopTask(9); // stop task number 9
```

Action(nSound, nDisplay, nMovement, nRepeat, nTime) Function - Spy

Built-in ROM subroutine number 44. This subroutine plays any combination of sound, LED animation, and movement, like a multimedia presentation. nSound is the sound to play (0-79, -1 means no sound). nDisplay is the LED animation to play (0-15, -1 means no animation). nMovement is the Spybot motion (see BasicMove, FancyMove, RandomMove, SlowDownMove, and SpeedUpMove) with -1 meaning no movement. nRepeat is the number of times to repeat the motion. nTime is the time to wait if nMovement equals -1, otherwise it is passed on to the movement subroutines.

```
Action(SOUND_GEIGER, ANIMATION_FLASH, -1, 0, 300);
```

Disp(display)

Function - Spy

Built-in ROM subroutine number 42. This subroutine displays one of the LED animations. Passing an undefined user animation will turn the display off (8-15).

```
Disp(ANIMATION_FLASH);
```

BasicMove(move, time)

Function - Spy

Built-in ROM subroutine number 43. This subroutine performs the requested motion for the specified duration. The motors are not floated or braked and motor power is not restored on exit.

```
BasicMove(MOVE_BASIC_AVOID_LEFT, 500);
```

Basic Motion Constants

```
MOVE_BASIC_FORWARD, MOVE_BASIC_BACKWARD,  
MOVE_BASIC_SPIN_LEFT, MOVE_BASIC_SPIN_RIGHT,  
MOVE_BASIC_TURN_LEFT, MOVE_BASIC_TURN_RIGHT,  
MOVE_BASIC_AVOID_LEFT, MOVE_BASIC_AVOID_RIGHT,  
MOVE_BASIC_REST, MOVE_BASIC_STOP
```

FancyMove(move, time)

Function - Spy

Built-in ROM subroutine number 47. This subroutine performs the requested motion for the specified duration. The motors are not floated or braked and motor power is not restored on exit.

```
FancyMove(MOVE_FANCY_ZIGZAG, 500);
```

Fancy Motion Constants

```
MOVE_FANCY_ZIGZAG, MOVE_FANCY_SHAKE, MOVE_FANCY_SCAN,  
MOVE_FANCY_STEP, MOVE_FANCY_STEP_BACK, MOVE_FANCY_SEARCH,  
MOVE_FANCY_FAKE_LEFT, MOVE_FANCY_RAKE_RIGHT,  
MOVE_FANCY_BUG_FORWARD, MOVE_FANCY_LAZY, MOVE_FANCY_WALK,  
MOVE_FANCY_WALK_BACK, MOVE_FANCY_DANCE
```

RandomMove(move, time)

Function - Spy

Built-in ROM subroutine number 46. This subroutine performs the requested motion for the specified duration. The motors are not floated or braked and motor power is not restored on exit.

```
RandomMove(MOVE_RANDOM_FORWARD, 500);
```

Random Motion Constants

```
MOVE_RANDOM_FORWARD, MOVE_RANDOM_BACKWARD,  
MOVE_RANDOM_SPIN_LEFT, MOVE_RANDOM_SPIN_RIGHT,  
MOVE_RANDOM_TURN_LEFT, MOVE_RANDOM_TURN_RIGHT,  
MOVE_RANDOM_REST
```

SlowDownMove(move, time)

Function - Spy

Built-in ROM subroutine number 48. This subroutine performs the requested motion for the specified duration. The motors are not floated or braked and motor power is not restored on exit.

```
SlowDownMove(MOVE_SLOWDOWN_FORWARD, 500);
```

SlowDown Motion Constants

```
MOVE_SLOWDOWN_FORWARD, MOVE_SLOWDOWN_BACKWARD,  
MOVE_SLOWDOWN_SPIN_LEFT, MOVE_SLOWDOWN_SPIN_RIGHT
```

SpeedUpMove(move, time)

Function - Spy

Built-in ROM subroutine number 49. This subroutine performs the requested motion for the specified duration. The motors are not floated or braked and motor power is not restored on exit.

```
SpeedUpMove(MOVE_SPEEDUP_FORWARD, 500);
```

SpeedUp Motion Constants

```
MOVE_SPEEDUP_FORWARD, MOVE_SPEEDUP_BACKWARD,  
MOVE_SPEEDUP_SPIN_LEFT, MOVE_SPEEDUP_SPIN_RIGHT
```

Sum2Mem(mem, value)

Function - Spy

Built-in ROM subroutine number 50. This subroutine adds value to a 2-byte location in EEPROM. The value is stored low byte first. No overflow checking is performed.

```
Sum2Mem(50, 400);
```

Sum4Mem(mem, value)

Function - Spy

Built-in ROM subroutine number 51. This subroutine adds value to a 4-byte location in EEPROM. The value is stored least significant byte first. No overflow checking is performed.

```
Sum4Mem(50, 400);
```

SendAllRangeMessage (nMessage, nData)

Function - Spy

Built-in ROM subroutine number 38. This subroutine sends nMessage to all Spybots in the world relation table that are in the here, there, or anywhere zones with the actual Spybot range as the high byte of each message.

```
SendAllRangeMessage(50, 40);
```

SendRCXMessage (nMessage)

Function - Spy

Built-in ROM subroutine number 37. This subroutine sends an RCX message at 2400 baud with bi-phase encoding and sum checksum. These messages can be received by an RCX or Scout.

```
SendRCXMessage(50);
```

SendSpybotMessage(nIndex, nCmd, nHiByte, nLoByte) Function - Spy

Built-in ROM subroutine number 34. This subroutine sends a message to a Spybot. If nIndex is a controller or PC then it does nothing. nIndex is the index of the Spybot in the world relation table (0-15), INDEX_LINKCAST, or INDEX_BROADCAST.

```
SendSpybotMessage(INDEX_LINKCAST, 50, 0, 10);
```

3.16 Swan Specific Features

SetMotorPowerSigned(const int motor, const int &v)

Function - Swan

Set the power of a motor to the specified signed value.

```
SetMotorPowerSigned(MTR_A, 10);
```

The motor can be specified using the following constants.

<u>Motor Constant</u>	<u>Meaning</u>
MTR_A	output A
MTR_B	output B
MTR_C	output C
MTR_D	virtual output D
MTR_E	virtual output E
MTR_F	virtual output F

There are additional constants for the motor power functions and values.

<u>Motor Power Direction</u>	<u>Meaning</u>
MPD_FWD	foward
MPD_REV	reverse
MPD_FLOAT	float
MPD_OFF	off
<u>Motor State</u>	<u>Meaning</u>
MS_FLOAT	float state
MS_BRAKE	brake state
MS_FWD	forward state
MS_REV	reverse state
<u>Motor Forward Power</u>	<u>Meaning</u>
MTR_FWD_POWER_1	forward at power level 1
MTR_FWD_POWER_2	forward at power level 2
MTR_FWD_POWER_3	forward at power level 3
MTR_FWD_POWER_4	forward at power level 4
MTR_FWD_POWER_5	forward at power level 5
MTR_FWD_POWER_6	forward at power level 6
MTR_FWD_POWER_7	forward at power level 7
MTR_FWD_POWER_8	forward at power level 8
<u>Motor Reverse Power</u>	<u>Meaning</u>
MTR_REV_POWER_1	reverse at power level 1
MTR_REV_POWER_2	reverse at power level 2
MTR_REV_POWER_3	reverse at power level 3
MTR_REV_POWER_4	reverse at power level 4
MTR_REV_POWER_5	reverse at power level 5
MTR_REV_POWER_6	reverse at power level 6
MTR_REV_POWER_7	reverse at power level 7
MTR_REV_POWER_8	reverse at power level 8
<u>Motor Float Power</u>	<u>Meaning</u>
MTR_FLOAT_POWER_1	float at power level 1
MTR_FLOAT_POWER_2	float at power level 2
MTR_FLOAT_POWER_3	float at power level 3
MTR_FLOAT_POWER_4	float at power level 4
MTR_FLOAT_POWER_5	float at power level 5
MTR_FLOAT_POWER_6	float at power level 6
MTR_FLOAT_POWER_7	float at power level 7
MTR_FLOAT_POWER_8	float at power level 8
<u>Motor Brake Power</u>	<u>Meaning</u>
MTR_BRAKE_POWER_1	brake at power level 1
MTR_BRAKE_POWER_2	brake at power level 2

MTR_BRAKE_POWER_3 brake at power level 3
MTR_BRAKE_POWER_4 brake at power level 4
MTR_BRAKE_POWER_5 brake at power level 5
MTR_BRAKE_POWER_6 brake at power level 6
MTR_BRAKE_POWER_7 brake at power level 7
MTR_BRAKE_POWER_8 brake at power level 8

MotorPowerSigned(const int motor)

Value - Swan

Read the signed power setting of a motor.

```
x = MotorPowerSigned(MTR_A);
```

SetMotorBrakePower(const int motor, const int &v)

Function - Swan

Set the brake power of a motor to the specified value.

```
SetMotorBrakePower(MTR_A, 10);
```

MotorBrakePower(const int motor)

Value - Swan

Read the brake power setting of a motor.

```
x = MotorBrakePower(MTR_A);
```

SetMotorPower8(const int motor, const int &v)

Function - Swan

Set the power of a motor to the specified value (using a scale from 0 to 7).

```
SetMotorPower8(MTR_A, 7);
```

MotorPower8(const int n)

Value - Swan

Read the power setting of a motor (using a scale from 0 to 7).

```
x = MotorPower8(MTR_A);
```

SetMotorPower128(const int motor, const int &v)

Function - Swan

Set the power of a motor to the specified value (using a scale from 0 to 127).

```
SetMotorPower128(MTR_A, 100);
```

MotorPower128(const int n)

Value - Swan

Read the power setting of a motor (using a scale from 0 to 127).

```
x = MotorPower128(MTR_A);
```

SetEventType(const int n, const int &v)

Function - Swan

Set the event type of event n to the type specified by v.

```
SetEventType(MyEvent, EVENT_TYPE_PRESSED);
```

EventType(const int n)

Value - Swan

Read the event type of an event.

```
x = EventType(MyEvent);
```

SetEventSrc(const int n, const int &v)

Function - Swan

Set the event source of event n to the source specified by v.

```
SetEventSrc(MyEvent, EST_SENSOR_1);
```

<u>Event Source</u>	<u>Meaning</u>
EST_SENSOR_1	sensor 1 source
EST_SENSOR_2	sensor 2 source
EST_SENSOR_3	sensor 3 source
EST_TIMER_1	timer 1 source
EST_TIMER_2	timer 2 source
EST_TIMER_3	timer 3 source
EST_TIMER_4	timer 4 source
EST_LAST_IR_MSG	IR msg source
EST_COUNTER_1	counter 1 source
EST_COUNTER_2	counter 2 source
EST_COUNTER_3	counter 3 source
EST_USER_EVENT_0	user event source
EST_USER_EVENT_1	user event source
EST_USER_EVENT_2	user event source
EST_USER_EVENT_3	user event source
EST_USER_EVENT_4	user event source
EST_VIRTUAL_MOTOR	virtual motor source
EST_VIRTUAL_SENSOR	virtual sensor source
EST_WAIT_FOR_MSG	IR msg source
EST_INFRARED_STATUS	IR msg source
EST_SENSOR_UNUSED	sensor source

EventSrc(const int n)

Value - Swan

Read the event source of an event.

```
x = EventSrc(MyEvent);
```

There are also constants for event states

<u>Event Source</u>	<u>Meaning</u>
ES_BELOW_LOWER	below lower threshold
ES_BETWEEN	between lower and upper thresholds
ES_ABOVE_UPPER	above upper threshold
ES_UNDETERMINED	undetermined state

SetEventCounts(const int n, const int &v) Function - Swan

Set the event count of event n to the count specified by v.

```
SetEventCounts(MyEvent, 10);
```

EventCounts(const int n) Value - Swan

Read the event counts of an event.

```
x = EventCounts(MyEvent);
```

ResetMSTimer(const int n) Function - Swan

Set the specified 1 ms timer back to zero.

```
ResetMSTimer(T1);
```

MSTimer(const int n) Value - Swan

Read the specified 1 ms timer value.

```
x = MSTimer(T1); // get the value of timer 1
```

WaitMS(const int &v) Function - Swan

Wait for the specified number of milliseconds.

```
WaitMS(T1);
```

System(const int n) Value - Swan

Read the specified system value.

```
x = System(SYS_BATTERY_LEVEL); // get the system value
```

SetSystem(const int n, const int &v) Function - Swan

Set the system item to the specified value.

```
SetSystem(SYS_OPCODES_PER_TIMESLICE, 10);
```

System Constants

Meaning

SYS_BATTERY_LEVEL	battery level
SYS_DEBUG_TASK_MODE	debug task mode
SYS_MEMORY_MAP_ADDRESS	memory map address
SYS_CURRENT_TASK	current task
SYS_SERIAL_LINK_STATUS	serial link status
SYS_OPCODES_PER_TIMESLICE	opcodes per timeslice
SYS_MOTOR_TRANSITION_DELAY	motor transition delay
SYS_SENSOR_REFRESH_RATE	sensor refresh rate
SYS_EXPANDED_RC_MESSAGES	expanded remote control messages
SYS_LCD_REFRESH_RATE	LCD refresh rate
SYS_NO_POWER_DOWN_ON_AC	power down while on AC
SYS_DEFAULT_TASK_STACK_SIZE	default task size
SYS_TASK_ACQUIRE_PRIORITY	task acquire priority
SYS_TRANSMITTER_RANGE	transmitter range
SYS_FLOAT_DURING_INACTIVE_PWM	float motors during inactive PWM
SYS_ROT_ERRORS_COUNT	rotation sensor errors count
SYS_ROT_DEBOUNCED_GLITCHES	rotation sensor debounce glitches
SYS_PREAMBLE_SIZE	preamble size
SYS_UNSOLICITED_MESSAGE	unsolicited messages
SYS_EXPANDED_SUBROUTINES	expanded subroutines
SYS_POWER_DOWN_DELAY	power down delay
SYS_WATCH_FORMAT	watch format
SYS_SENSOR_MISSED_CONVERSIONS	sensor missed conversions
SYS_IGNORE_MESSAGES_CPU	ignore messages CPU
SYS_COMM_ERRORS_TIMEOUT	count of timeout errors
SYS_COMM_ERRORS_PARITY	count of parity errors
SYS_COMM_ERRORS_FRAMING	count of framing errors
SYS_COMM_ERRORS_OVERRUN	count of overrun errors
SYS_INTER_CHAR_TIMEOUT	inter-character timeout
SYS_TASK_SCHEDULING_PRIORITY	task scheduling priority
SYS_VOLUME	volume level
SYS_SOUND_PLAYING	sound playing state
SYS_PLAY_SOUNDS	enable/disable sound playing
SYS_QUEUED_SOUND_COUNT	count of sounds waiting to be played
SYS_SENSOR_STARTUP_DELAY	sensor startup delay
SYS_SENSOR_DELAY_CYCLES	sensor delay cycles
SYS_SENSOR_REFRESH_STATE	sensor refresh state
SYS_SENSOR_SCAN_COUNT	sensor scan count
SYS_DATALOG_SIZE	datalog size

ImmediateBatteryLevel()

Value - Swan

Read the immediate battery level.

```
x = ImmediateBatteryLevel();
```

DebugTaskMode()

Value - Swan

Read the debug task mode.

```
x = DebugTaskMode();
```

MemoryMapAddress()

Value - Swan

Read the memory map address.

```
x = MemoryMapAddress();
```

CurrentTask()

Value - Swan

Read the current task number.

```
x = CurrentTask();
```

SerialLinkStatus()

Value - Swan

Read the serial link status.

```
x = SerialLinkStatus();
```

Serial Link Status Constants

SLS_WAIT_FOR_MSG
SLS_RECEIVING_MSG
SLS_TRANSMITTING
SLS_UNKNOWN

Meaning

waiting for message
receiving message
transmitting
unknown

OpcodesPerTimeslice()

Value - Swan

Read the number of opcodes to execute per timeslice.

```
x = OpcodesPerTimeslice();
```

SetOpcodesPerTimeslice(const int &v)

Function - Swan

Set the system item to the specified value.

```
SetOpcodesPerTimeslice(10);
```

MotorTransitionDelay()

Value - Swan

Read the number of milliseconds to delay when changing motor direction.

```
x = MotorTransitionDelay();
```

SetMotorTransitionDelay(const int &v)

Function - Swan

Set the motor transition delay to the specified value.

```
SetMotorTransitionDelay(10);
```

SensorRefreshRate()

Value - Swan

Read the sensor refresh rate.

```
x = SensorRefreshRate();
```

SetSensorRefreshRate(const int &v)

Function - Swan

Set the sensor refresh rate to the specified value.

```
SetSensorRefreshRate(10);
```

ExpandedRemoteMessages()

Value - Swan

Read a boolean value indicating whether or not to support expanded remote control messages.

```
x = ExpandedRemoteMessages(); // 0 or 1
```

SetExpandedRemoteMessages(const int &v)

Function - Swan

Enable or disable expanded remote control messages.

```
SetExpandedRemoteMessages(false);
```

LCDRefreshRate()

Value - Swan

Read the LCD refresh rate.

```
x = LCDRefreshRate();
```

SetLCDRefreshRate(const int &v)

Function - Swan

Set the LCD refresh rate.

```
SetLCDRefreshRate(10);
```

NoPowerDownOnAC()

Value - Swan

Read a boolean value specifying whether or not to power down while running on AC power.

```
x = NoPowerDownOnAC();
```

SetNoPowerDownOnAC(const int &v)

Function - Swan

Enable or disable power down while running on AC power.

```
SetNoPowerDownOnAC(false);
```

DefaultStackSize()

Value - Swan

Read the default stack size.

```
x = DefaultStackSize();
```

SetDefaultStackSize(const int &v)

Function - Swan

Set the default stack size.

```
SetDefaultStackSize(10);
```

TaskAcquirePriority()

Value - Swan

Read the task acquire priority level.

```
x = TaskAcquirePriority();
```

SetTaskAcquirePriority(const int &v)

Function - Swan

Set the task acquire priority level.

```
SetTaskAcquirePriority(10);
```

TransmitterRange()

Value - Swan

Read the transmitter range value.

```
x = TransmitterRange();
```

FloatDuringInactivePWM() **Value - Swan**

Read a boolean value specifying whether or not to float motors during inactive pulse width modulation.

```
x = FloatDuringInactivePWM();
```

SetFloatDuringInactivePWM(const int &v) **Function - Swan**

Enable or disable floating the motors during inactive pulse width modulation.

```
SetFloatDuringInactivePWM(false);
```

RotErrorsCount() **Value - Swan**

Read the rotation sensor errors count.

```
x = RotErrorsCount();
```

RotDebouncedGlitches() **Value - Swan**

Read the rotation sensor debounced glitches.

```
x = RotDebouncedGlitches();
```

SystemPreambleSize() **Value - Swan**

Read the system preamble size.

```
x = SystemPreambleSize();
```

SetSystemPreambleSize(const int &v) **Function - Swan**

Set the system preamble size.

```
SetSystemPreambleSize(10);
```

UnsolicitedMessages() **Value - Swan**

Read a boolean value specifying whether or not to accept unsolicited messages.

```
x = UnsolicitedMessages();
```

ExpandedSubroutines()

Value - Swan

Read a boolean value specifying whether or not to allow an expanded number of subroutines.

```
x = ExpandedSubroutines();
```

SetExpandedSubroutines(const int &v)

Function - Swan

Enable or disable support for an expanded number of subroutines.

```
SetExpandedSubroutines(false);
```

PowerDownDelay()

Value - Swan

Read the power down delay.

```
x = PowerDownDelay();
```

WatchFormat()

Value - Swan

Read the watch format.

```
x = WatchFormat();
```

SetWatchFormat(const int &v)

Function - Swan

CommErrorsTimeout()

Value - Swan

Read the number of communication timeout errors.

```
x = CommErrorsTimeout();
```

CommErrorsParity()

Value - Swan

Read the number of communication parity errors.

```
x = CommErrorsParity();
```

CommErrorsFraming()

Value - Swan

Read the number of communication framing errors.

```
x = CommErrorsFraming();
```

CommErrorsOverrun()

Value - Swan

Read the number of communication overrun errors.

```
x = CommErrorsOverrun();
```

InterCharTimeout()

Value - Swan

Read the inter-character timeout value.

```
x = InterCharTimeout();
```

SetInterCharTimeout(const int &v)

Function - Swan

Set the inter-character timeout value.

```
SetInterCharTimeout(10);
```

TaskSchedulingPriority()

Value - Swan

Read the task scheduling priority.

```
x = TaskSchedulingPriority();
```

SetTaskSchedulingPriority(const int &v)

Function - Swan

Set the task scheduling priority.

```
SetTaskSchedulingPriority(10);
```

Volume()

Value - Swan

Read the system volume level.

```
x = Volume();
```

SetVolume(const int &v)

Function - Swan

Set the system volume level. The maximum volume level is MAX_VOLUME.

```
SetVolume(10);
```

SoundActive()

Value - Swan

Read a boolean value specifying whether or not a sound is currently playing.

```
x = SoundActive();
```

PlaySounds()

Value - Swan

Read a boolean value specifying whether or not to allow sound playing.

```
x = PlaySounds();
```

SetPlaySounds(const int &v)

Function - Swan

Enable or disable support for playing sounds.

```
SetPlaySounds(false);
```

QueuedSoundCount()

Value - Swan

Read the number of sounds currently waiting to be played.

```
x = QueuedSoundCount();
```

SensorStartupDelay()

Value - Swan

Read the sensor startup delay.

```
x = SensorStartupDelay();
```

SetSensorStartupDelay(const int &v)

Function - Swan

Set the sensor startup delay.

```
SetSensorStartupDelay(10);
```

SensorDelayCycles()

Value - Swan

Read the number of sensor delay cycles.

```
x = SensorDelayCycles();
```

SensorRefreshState()

Value - Swan

Read the sensor refresh state.

```
x = SensorRefreshState();
```

SensorScanCount()

Value - Swan

Read the sensor scan count.

```
x = SensorScanCount();
```

DatalogSize()

Value - Swan

Read the datalog size.

```
x = DatalogSize();
```

IntrinsicIndGlobal(const int n)

Value - Swan

Access the value of an intrinsic indirectly.

```
x = IntrinsicIndGlobal(15);
```

GlobalVar(const int &n)

Value - Swan

Read or write the value of a global variable (either directly or indirectly).

```
x = GlobalVar(y);
```

StackAddress(const int task)

Value - Swan

Read the stack address of the specified task.

```
x = StackAddress(1);
```

StackSize(const int task)

Value - Swan

Read the size of the stack for the specified task.

```
x = StackSize(1);
```

ClearAll(const int &v)

Function - Swan

Clear the specified items. The constants can be added together to clear multiple items at once.

```
ClearAll(CLR_TIMERS);
```

ClearAll Constants

Meaning

CLR_TIMERS	clear all timers
CLR_INPUTS	clear all inputs
CLR_VARIABLES	clear all variables
CLR_TASK_STACK	clear all task stacks
CLR_EVENTS	clear all events
CLR_BREAKPOINTS	clear all breakpoints
CLR_DATALOG	clear the datalog

BitSet(const int &result, const int &operand)

Function - Swan

Set the bit in the result specified by the operand.

```
BitSet(x, 0x01);
```

BitClear(const int &result, const int &operand)

Function - Swan

Clear the bit in the result specified by the operand.

```
BitClear(x, 0x01);
```

Negate(const int &result, const int &operand)

Function - Swan

Negate the bits in the result specified by the operand.

```
Negate(x, 0x01);
```

4 Technical Details

This section explains some of the low-level features of NQC. In general, these mechanisms should only be used as a last resort since they may change in future releases. Most programmers will never need to use the features described below - they are mainly used in the creation of the NQC API file.

4.1 The asm statement

The `asm` statement is used to define almost all of the NQC API calls. The syntax of the statement is:

```
asm { item1, item2 ... itemN }
```

Where an item is one of the following

```
constant_expression
$ expression
$ expression : restrictor
```

The statement simply emits the values of each of the items as raw bytecodes. Constant items are the simplest - they result in a single byte of raw data (the lower 8 bits of the constant value). For example, the API file defines the following inline function:

```
void ClearMessage() { asm { 0x90 }; }
```

Whenever `ClearMessage()` is called by a program, the value `0x90` is emitted as a bytecode.

Many API functions take arguments, and these arguments must be encoded into an appropriate effective address for the bytecode interpreter. In the most general case, an effective address contains a *source code* followed by a two byte value (least significant byte first). Source codes are explained in the SDK documentation available from LEGO. However, it is often desirable to encode the value in some other manner - for example to use only a single byte value after the source code, omit the source code itself, or only allow certain sources to be used. A *restrictor* may be used to control how the effective address is formatted. A restrictor is a 32 bit constant value. The lower 24 bits form a bitmask indicating which sources are valid (bit 0 should be set to allow source 0, etc).

The upper 8 bits include formatting flags for the effective address. Note that when no restrictor is specified, this is the same as using a restrictor of 0 (no restriction on sources, and a format of source followed by two value bytes). The API file defines the following constants which can be used to build restrictors:

```
#define __ASM_SMALL_VALUE  0x01000000
#define __ASM_NO_TYPE      0x02000000
#define __ASM_NO_LOCAL     0x04000000

#if __RCX==2
    // no restriction
    #define __ASM_SRC_BASIC  0
    #define __ASM_SRC_EXT   0
#else
    #define __ASM_SRC_BASIC  0x000005
    #define __ASM_SRC_EXT   0x000015
#endif
```

The `__ASM_SMALL_VALUE` flag indicates that a one-byte value should be used instead of a two-byte value. The `__ASM_NO_TYPE` flag indicates that the source code should be omitted. The `__ASM_NO_LOCAL` flag specifies that local variables are not a legal source for the expression. Note that the RCX2 firmware is less restrictive than the other interpreters, thus the definition of `__ASM_SRC_BASIC` and `__ASM_SRC_EXT` are relaxed in the RCX2 case. The API definition file for NQC contains numerous examples of using restrictors within asm statement. If you are using a command-line version of NQC, you can emit the API file by typing the following command:

```
nqc -api
```

4.2 Data Sources

The bytecode interpreters use different data sources to represent the various kinds of data (constants, variables, random numbers, sensor values, etc). The specific sources depend

to a certain extent on which device you are using and are described in the SDK documentation available from LEGO.

NQC provides a special operator to represent a data source:

```
@ constant
```

The value of this expression is the data source described by the constant. The lower 16 bits of the constant represent the data value, and the next 8 bits are the source code. For example, the source code for a random number is 4, so the expression for a random number between 0 and 9 would be:

```
@0x40009
```

The NQC API file defines a number of macros which make the use of the @ operator transparent to the programmer. For example, in the case of random numbers:

```
#define Random(n) @(0x40000 + (n))
```

Note that since source 0 is the global variable space, the global storage locations can be referenced by number: @0 refers to storage location 0. If for some reason you need explicit control over where variables are being stored, then you should use `#pragma reserve` to instruct NQC not to use those storage locations, and then access them manually with the @ operator. For example, the following code snippet reserves location 0 and creates a macro for it called `x`.

```
#pragma reserve 0
#define x (@0)
```

Because of how sensors have been implemented it is necessary to convert the sensor's data source into a sensor index for use in macros such as `SensorValueRaw()`. The `__sensor` expression can be used to do this:

```
#define SensorValueRaw(n) @(0xc0000 + (__sensor(n)))
```